



### DESCRIPTION

The MP2772 is a highly integrated, switching battery charger that provides a complete solution for wearable and portable devices. The device provides an 8-bit successive approximation register (SAR) analog-to-digital converter (ADC) for battery and system monitoring, smart power path management, narrow-voltage DC (NVDC) charging, push-button control, integrated load switches with an individual enable function, and an autonomous battery charging profile.

The MP2772 integrates a battery charger, boost converter, and two embedded load switches into a single device. Only one inductor is required to charge a battery or boost the battery voltage to charge the device through load switches. The device achieves a low quiescent current ( $I_Q$ ) down to 5 $\mu$ A in shipping mode and provides a low  $I_Q$  for battery self-life extension in light-load boost operation. The integrated ADC monitors battery charging parameters and load parameters during boost operation.

The MP2772 provides various safety features for battery charging and system operations, including the charge safety timer, battery and junction temperature ( $T_J$ ) monitoring, over-voltage protection (OVP), and over-current protection (OCP). If a fault condition occurs, the device asserts an interrupt signal to the microcontroller unit (MCU) host.

The MP2772 also provides battery MOSFET disable control to enter shipping mode and reset the system via the /DISC pin.

The MP2772 is available in a WLCSP-30 (2.5mmx2.85mm) package.

### FEATURES

- High-Performance Buck Charger:
  - Up to 6.5V Operating Input Voltage ( $V_{IN}$ )
  - 26V Sustainable  $V_{IN}$
  - Charge Efficiency is >95% at 0.5A and >94% at 1A ( $V_{IN} = 5V$ )
  - $\pm 0.5\%$  Charge Voltage Regulation Accuracy

### FEATURES (continued)


- 100mA to 3.2A I<sup>2</sup>C-Configurable Input Current Limit Compatible with BC1.2
- 20mA to 2A I<sup>2</sup>C-Configurable Charge Current with 20mA/Step Resolution
- Down to 10mA Termination Current
- Boost Operation:
  - Low- $I_Q$ , Light-Load Boost Operation
  - Automatic Transition from Buck to Boost
  - Up to 6V I<sup>2</sup>C-Configurable Boost Output with 0.1V/Step Resolution
  - Up to 1.5A of  $I_{OUT}$  in OTG Mode
- Safety:
  - Safety Timers for Fast Charge, Pre-Charge, and Watchdog
  - I<sup>2</sup>C-Configurable JEITA Profile for Safety Operation
  - Adjustable Thermal Regulation Loop and Thermal Shutdown Protection
  - Input, Battery, and System OVP
- Dual, Integrated Load Switches with OCP and Short-Circuit Protection (SCP)
- Integrated ADC for Charge and Discharge Parameters
- NVDC Power Path Enabling System Instant Start-Up with Deeply Discharged Battery
- Battery Supplement Mode Provides Battery Current to Support Heavy System Loads
- Below 5 $\mu$ A Battery Discharge Current in Shipping Mode
- Integrated, 30m $\Omega$ , Low- $R_{DS(ON)}$  Battery MOSFET (BATFET) with Shipping Mode and System Power Reset Function
- Available in a Small WLCSP-30 (2.5mmx2.85mm) Package

### APPLICATIONS

- Wearable Devices
- Earbud Charging Cases
- Headsets and Headphones
- Internet of Things (IoT) Devices

All MPS parts are lead-free, halogen-free, and adhere to the RoHS directive. For MPS green status, please visit the MPS website under Quality Assurance. "MPS", the MPS logo, and "Simple, Easy Solutions" are trademarks of Monolithic Power Systems, Inc. or its subsidiaries.

TYPICAL APPLICATION



### ORDERING INFORMATION

Part Number*	Package	Top Marking	MSL Rating
MP2772GC-xxxx**	WLCSP-30 (2.5mmx2.85mm)	See Below	1
EVKT-MP2772	Evaluation kit		

\* For Tape & Reel, add suffix -Z (e.g. MP2772GC-xxxx-Z).

\*\* “xxxx” is the register setting option. The factory default is “0000”. The content can be viewed in the register map. Contact an MPS FAE to obtain an “xxxx” value.

### TOP MARKING

**MPYYWW**  
**MP2772**  
**LLLLLL**  
**AABBID**

MP: MPS prefix  
 YY: Year code  
 WW: Week code  
 MP2772: Part Number  
 LLLLLL: Lot number  
 AABB: Die ID in X axis and Y axis  
 ID: Wafer

### EVALUATION KIT EVKT-MP2772

EVKT-MP2772 kit contents (items below can be ordered separately):

#	Part Number	Item	Quantity
1	EVL2772-C-00A	MP2772 evaluation board	1
2	EVKT-USB2C-02-BAG	Includes one USB-to-I <sup>2</sup> C communication interface, one USB cable, and one ribbon cable	1
3	Online resources	Include datasheet, user guide, product brief, and GUI	1

Order directly from [MonolithicPower.com](http://MonolithicPower.com) or our distributors.





Figure 1: EVKT-MP2772 Evaluation Kit Set-Up

**PACKAGE REFERENCE**



**PIN FUNCTIONS**

Pin #	Name	Description
A1	PGND	<b>Power ground.</b>
B1	AGND	<b>Analog ground.</b>
A2, B2	SW	<b>Switching node.</b> Connect the SW pin to the inductor.
A3, B3	PMID	<b>Internal power.</b> Bypass the PMID pin by connecting a 10 $\mu$ F capacitor between the PMID and PGND pins, placed as close as possible to the IC.
A4, B4	VIN	<b>Power input.</b> Bypass the VIN pin by connecting a minimum 1 $\mu$ F capacitor between the VIN and PGND pins.
A5	BOOST2	<b>Boost load switch mode output 2.</b> Place a 2.2 $\mu$ F to 4.7 $\mu$ F capacitor between the BOOST2 and PGND pins.
B5	BOOST1	<b>Boost load switch mode output 1.</b> Place a 2.2 $\mu$ F to 4.7 $\mu$ F capacitor between the BOOST1 and PGND pins.
C1	DP	<b>Positive pin of the USB data line pair.</b>
C2	DM	<b>Negative pin of the USB data line pair.</b>
C3	BST	<b>Bootstrap power for driving the high-side MOSFET (HS-FET).</b> Connect a 47nF bootstrap capacitor ( $C_{BST}$ ) between the BST and SW pins to form a floating supply for the HS-FET driver.
C4	VCC	<b>Internal LDO output.</b> Connect the VCC pin to a 2.2 $\mu$ F capacitor.
C5	ILIM	<b>Input current limit configuration.</b> Pull the ILIM pin logic high to set the input current limit ( $I_{IN\_LIMIT}$ ) to 2.5A; pull ILIM logic low to set $I_{IN\_LIMIT}$ to 0.5A.
D1, E1, F1	BAT	<b>Battery positive terminal.</b> The internal NVDC battery MOSFET is connected between the BAT and SYS pins. Place a minimum 10 $\mu$ F ceramic capacitor between BAT and PGND.
D2, E2, F2	SYS	<b>System power supply.</b> Place a 10 $\mu$ F ceramic capacitor between the SYS and PGND pins.
D3	NTC	<b>Temperature sense input.</b> Connect the NTC pin to a negative temperature coefficient (NTC) thermistor.
D4	/DISC	<b>Shipping mode entry and system power reset control.</b> Toggle the /DISC pin low to perform battery MOSFET reset or enter shipping mode.
D5	CAP	<b>External capacitor for charge pump power storage.</b> Place a 100nF capacitor between the CAP and AGND pins.
E3	/CE	<b>Enable for battery charging.</b> Pull the /CE pin low to enable charging. /CE is low by default, and the pin can be disabled via the PIN_CTRL_EN bit (01h, bit[4]).
E4	SDA	<b>I<sup>2</sup>C interface data.</b> Connect the SDA pin to the logic rail via a 10k $\Omega$ resistor.
E5	BST_EN	<b>Enable for boost switching.</b> Pull the BST_EN pin high to enable the boost function. BST_EN is low by default, and the pin can be disabled via the PIN_CTRL_EN bit.
F3	VNTC	<b>Reference voltage output.</b> The VNTC pin powers up the NTC resistor dividers.
F4	/INT	<b>Open-drain interrupt output.</b> The /INT pin is high by default. A 256 $\mu$ s low pulse is generated on /INT when the IC has a status or fault report. Pull up /INT via a 10k $\Omega$ resistor.
F5	SCL	<b>I<sup>2</sup>C interface clock.</b> Connect the SCL pin to the logic rail via a 10k $\Omega$ resistor.

**ABSOLUTE MAXIMUM RATINGS** <sup>(1)</sup>

VIN to PGND .....	-0.3V to +26V <sup>(2)</sup>
PMID to PGND .....	-0.3V to +26V <sup>(2)</sup>
SW to PGND.....	-0.3V to +26V <sup>(2)</sup>
SYS to PGND .....	-0.3V to +6V
BATT to PGND.....	-0.3V to +5.5V
BOOST1, BOOST2 to PGND .....	-0.3V to +7.5V
CAP to AGND.....	-0.3V to +9V
BST to SW.....	-0.3V to +4V
VCC to AGND.....	-0.3V to +4V
All other pins to AGND.....	-0.3V to VCC + 0.3V
Junction temperature (T <sub>J</sub> ) .....	150°C
Lead temperature .....	260°C
Continuous power dissipation (T <sub>A</sub> = 25°C) <sup>(3)</sup>	2.5W

**ESD Ratings**

Human body model (HBM) .....	2000V
Charged-device model (CDM).....	500V

**Recommended Operating Conditions** <sup>(4)</sup>

Supply voltage (V <sub>IN</sub> ) .....	4V to 6.5V
System current (I <sub>SYS</sub> ).....	Up to 2.5A
Fast charge current (I <sub>CC</sub> ).....	Up to 2A
Battery discharge current (I <sub>DISCHG</sub> ) .....	Up to 4.5A
Battery voltage (V <sub>BATT</sub> ) .....	Up to 4.6V
Operating junction temp (T <sub>J</sub> )....	-40°C to +125°C

<b>Thermal Resistance</b> <sup>(5)</sup>	<b>θ<sub>JA</sub></b>	<b>θ<sub>JC</sub></b>
WLCSP-30 (2.5mmx2.85mm).....	68.5	0.4
	°C/W	

**Notes:**

- 1) Exceeding these ratings may damage the device.
- 2) These absolute maximum ratings are rated under room temperature.
- 3) The maximum allowable power dissipation is a function of the maximum junction temperature, T<sub>J</sub> (MAX), the junction-to-ambient thermal resistance, θ<sub>JA</sub>, and the ambient temperature, T<sub>A</sub>. The maximum allowable continuous power dissipation at any ambient temperature is calculated by P<sub>D</sub> (MAX) = (T<sub>J</sub> (MAX) - T<sub>A</sub>) / θ<sub>JA</sub>. Exceeding the maximum allowable power dissipation produces an excessive die temperature, which may cause the regulator to go into thermal shutdown. Internal thermal shutdown circuitry protects the device from permanent damage.
- 4) The device is not guaranteed to function outside of its operating conditions.
- 5) Measured on a JESD51-7, a 4-layer PCB.

## ELECTRICAL CHARACTERISTICS

$V_{IN} = 5V$ ,  $T_A = -40^{\circ}C$  to  $+125^{\circ}C$ , unless otherwise noted.

Parameters	Symbol	Condition	Min	Typ	Max	Units
<b>Quiescent Current</b>						
Battery discharge current in shipping mode	$I_{BAT\_SHIP}$	$V_{BATT} = 4V$ , $V_{IN} = 0V$ , battery MOSFET (BATFET) disabled, $T_A = 25^{\circ}C$		3	5	$\mu A$
		$V_{BATT} = 4V$ , $V_{IN} = 0V$ , BATFET disabled		3	10	$\mu A$
Input quiescent current during buck switching	$I_{IN\_BUCK}$	$V_{IN} = 5V$ , converter switching, $V_{BATT} = 3.8V$ , charge disabled, $I_{SYS} = 0A$ , $I_{BATT} = 0A$		5		mA
Input leakage current in buck high-impedance (Hi-Z) mode	$I_{IN\_SUSP}$	$V_{IN} = 5V$ , switching disabled, BATFET enabled, no load at SYS node		0.15	1	mA
Battery discharge current in boost discharging mode	$I_{Q\_BOOST}$	$V_{BATT} = 4V$ , boost switching, load switches enabled, on-the-go (OTG) mode disabled, no loading at BOOST1/BOOST2, watchdog timer disabled, BATFET over-current protection (OCP) disabled		300		$\mu A$
Battery discharge current in idle mode	$I_{Q\_IDLE}$	$V_{BATT} = 4V$ , $V_{IN} = 0V$ , watchdog timer disabled, BATFET enabled, BATFET OCP disabled, analog-to-digital converter (ADC) disabled		10	22	$\mu A$
<b>Input Power Characteristics</b>						
Input voltage operating range	$V_{IN\_OP}$		4		6.5	V
Input under-voltage lockout (UVLO) threshold	$V_{IN\_UVLO}$	$V_{IN}$ falling, $V_{BATT} = 0V$	2.95	3.2	3.45	V
Input UVLO threshold hysteresis	$V_{IN\_UVLO\_HYS}$	$V_{IN}$ rising, $V_{BATT} = 0V$		250		mV
Input vs. battery voltage headroom threshold	$V_{HDRM}$	$V_{IN}$ rising, $V_{BATT} = 3.8V$	80	200	320	mV
		$V_{IN}$ falling, $V_{BATT} = 3.8V$	30	100	170	mV
Input over-voltage lockout (OVLO) threshold	$V_{IN\_OVLO}$	$V_{IN}$ rising	6.25	6.5	6.75	V
Input OVLO threshold hysteresis	$V_{IN\_OVLO\_HYS}$	$V_{IN}$ falling		600		mV
<b>Low-Dropout (LDO) Regulator</b>						
VCC voltage ( $V_{CC}$ ) LDO output voltage	$V_{CC}$	$V_{IN} = 5V$ , $V_{BATT} = 3.8V$ , $I_{VCC} = 10mA$		3.6		V
VCC LDO output current upper limit	$I_{VCC}$	$V_{IN} = 5V$ , $V_{BATT} = 3.8V$ , $T_A = 0^{\circ}C$ to $70^{\circ}C$			10	mA
VCC LDO UVLO threshold	$V_{CC\_UVLO}$	$V_{IN}$ falling, $V_{BATT} = 0V$		2		V
VCC LDO UVLO hysteresis	$V_{CC\_UV\_HYS}$	$V_{IN}$ rising, $V_{BATT} = 0V$		250		mV

**ELECTRICAL CHARACTERISTICS (continued)**
**V<sub>IN</sub> = 5V, T<sub>A</sub> = -40°C to +125°C, unless otherwise noted.**

Parameters	Symbol	Condition	Min	Typ	Max	Units
<b>DC/DC Buck Switching</b>						
Minimum system regulation voltage range	V <sub>SYS_MIN</sub>		3.2		4.25	V
Minimum system regulation voltage accuracy	V <sub>SYS_MIN_REG_ACC</sub>	SYS_MIN_REG (07h, bits[3:1]) = b'010 (3.5V), V <sub>BATT</sub> < V <sub>SYS_MIN</sub> , V <sub>TRACK1</sub> = 150mV	3.5	3.65	3.8	V
Battery tracking voltage	V <sub>TRACK1</sub>	V <sub>BATT</sub> = 3.3V, V <sub>BATT</sub> < V <sub>SYS_MIN</sub> , SYS_MIN_REG = b'010 (3.5V)	85	150	215	mV
	V <sub>TRACK2</sub>	V <sub>BATT</sub> = 3.6V, V <sub>BATT</sub> > V <sub>SYS_MIN</sub> , SYS_MIN_REG = b'010 (3.5V)	45	100	155	mV
Blocking MOSFET on resistance	R <sub>DSON_QB</sub>			30		mΩ
High-side MOSFET (HS-FET) on resistance	R <sub>DSON_QHS</sub>			30		mΩ
Low-side MOSFET (LS-FET) on resistance	R <sub>DSON_QLS</sub>			60		mΩ
Buck switching frequency	f <sub>sw</sub>	FRE_SEL (00h, bit[2]) = b'1 (2MHz)	1820	2000	2150	kHz
		FRE_SEL = b'0 (1.5MHz)	1320	1500	1690	kHz
System over-voltage protection (OVP) trip threshold	V <sub>SYS_OVP_TRIP</sub>	V <sub>BATT</sub> = 4.2V, SYS_OVP_RI_TH (09h, bits[7:4]) = b'1010 (4800mV), SYS pin voltage (V <sub>sys</sub> ) rising	4.65	4.8	4.95	V
System OVP recovery threshold	V <sub>SYS_OVP_RCVY</sub>	V <sub>BATT</sub> = 4.2V, SYS_OVP_FL_TH (09h, bits[3:0]) = b'1000 (4600mV), V <sub>sys</sub> falling	4.45	4.6	4.75	V
System over-voltage (OV) discharge load	I <sub>sys_LOAD</sub>	SYS_OVP_RI_TH = b'1010, V <sub>sys</sub> = 5V		20		mA
<b>Load Switches</b>						
Load switch on resistance	R <sub>DSON_LDSW_QL</sub>			300		mΩ
	R <sub>DSON_LDSW_QR</sub>			300		mΩ
Load switch over-current (OC) threshold for each rail	I <sub>LDSW_OC</sub>	Buck mode, V <sub>PMID</sub> = 5V, load switch current rising, LDSW_OCP (0Eh, bits[1:0]) = b'01	310	550	820	mA
		Buck mode, V <sub>PMID</sub> = 5V, load switch current rising, LDSW_OCP = b'11	580	870	1150	mA
		Boost mode, V <sub>PMID</sub> = 5V, load switch current rising, LDSW_OCP = b'11	350	550		mA
Load switch short current limit	I <sub>LDSW_SC</sub>	V <sub>PMID</sub> = 5V, load switch output (BOOST1/BOOST2) short to PGND		15		mA

**ELECTRICAL CHARACTERISTICS (continued)**
**V<sub>IN</sub> = 5V, T<sub>A</sub> = -40°C to +125°C, unless otherwise noted.**

Parameters	Symbol	Condition	Min	Typ	Max	Units
<b>Battery Charging (T<sub>A</sub> = 0°C to 70°C)</b>						
Battery charge voltage regulation range	V <sub>BATT_REG_RANGE</sub>		3.6		4.6	V
Battery charge voltage step	V <sub>BATT_REG_STEP</sub>			10		mV
Battery charge voltage regulation accuracy	V <sub>BATT_REG_ACC</sub>	V <sub>BATT_REG</sub> = 3.6V, T <sub>A</sub> = 0°C to 70°C	-0.5		+0.5	% of V <sub>BATT_REG</sub>
		V <sub>BATT_REG</sub> = 4.2V, T <sub>A</sub> = 0°C to 70°C				
		V <sub>BATT_REG</sub> = 4.35V, T <sub>A</sub> = 0°C to 70°C				
Fast charge current range	I <sub>CC</sub>		20		2000	mA
Fast charge current step	I <sub>CC_STEP</sub>			20		mA
Fast charge current accuracy	I <sub>CC_ACC</sub>	I <sub>CC</sub> = 0.1A, I <sub>CC</sub> (04h, bits[7:1]) = b'0000100 (100mA), V <sub>BATT</sub> = 3.8V, T <sub>A</sub> = 0°C to 70°C	-25		+25	% of I <sub>CC</sub>
		I <sub>CC</sub> = 0.5A. I <sub>CC</sub> = b'0011000 (500mA), V <sub>BATT</sub> = 3.8V, T <sub>A</sub> = 0°C to 70°C	-10		+10	% of I <sub>CC</sub>
		I <sub>CC</sub> = 2.0A. I <sub>CC</sub> = b'1100011 (2A), V <sub>BATT</sub> = 3.8V, T <sub>A</sub> = 0°C to 70°C	-5		+5	% of I <sub>CC</sub>
Pre-charge to fast charge threshold range	V <sub>BATT_PRE_RANGE</sub>		2.4		3	V
Pre-charge to fast charge threshold step	V <sub>BATT_PRE_STEP</sub>			200		mV
Pre-charge to fast charge threshold accuracy	V <sub>BATT_PRE_ACC</sub>	V <sub>BATT</sub> rising, V <sub>PRE</sub> (03h, bits[2:1] = b'10 (2.8V)	2.65	2.8	2.95	V
Fast charge back to pre-charge threshold hysteresis	V <sub>BATT_PRE2CC_HYS</sub>	V <sub>BATT</sub> falling		200		mV
Trickle charge to pre-charge threshold	V <sub>BATT_TC2PRE</sub>	V <sub>BATT</sub> rising	2.05	2.2	2.35	V
Trickle charge to pre-charge threshold hysteresis	V <sub>BATT_TC_HYS</sub>	V <sub>BATT</sub> falling		200		mV
Pre-charge current range	I <sub>PRE_RANGE</sub>		10		160	mA
Pre-charge current step	I <sub>PRE_RANGE_STEP</sub>			10		mA
Pre-charge current accuracy	I <sub>PRE_ACC</sub>	V <sub>BATT</sub> = 2.5V, I <sub>PRE</sub> (05h, bits[7:4]) = b'1000 (50mA), T <sub>A</sub> = 0°C to 70°C	40	50	60	mA
		V <sub>BATT</sub> = 2.5V, I <sub>PRE</sub> = b'1111 (160mA), T <sub>A</sub> = 0°C to 70°C	140	160	180	mA
Trickle charge current range	I <sub>TC_RANGE</sub>		10		70	mA
Trickle charge current accuracy	I <sub>TC_ACC</sub>	V <sub>BATT</sub> = 1.8V, I <sub>TRICKLE</sub> (02h, bits[2:0]) = b'100 (50mA), T <sub>A</sub> = 0°C to 70°C	40	50	60	mA

**ELECTRICAL CHARACTERISTICS (continued)**
**V<sub>IN</sub> = 5V, T<sub>A</sub> = -40°C to +125°C, unless otherwise noted.**

Parameters	Symbol	Condition	Min	Typ	Max	Units
Charge termination current threshold range	I <sub>TERM_RANGE</sub>		10		160	mA
Charge termination current threshold accuracy	I <sub>TERM_ACC</sub>	I <sub>TERM</sub> (05h, bits[3:0]) = b'000 (10mA), V <sub>BATT_REG</sub> = 4.2V, TERM_EN (00h, bit[1]) = b'1, T <sub>A</sub> = 0°C to 70°C	5	10	15	mA
Charge termination current threshold accuracy	I <sub>TERM_ACC</sub>	I <sub>TERM</sub> = b'100 (50mA), V <sub>BATT_REG</sub> = 4.2V, TERM_EN = b'1, T <sub>A</sub> = 0°C to 70°C	35	50	65	mA
		I <sub>TERM</sub> = b'1111 (160mA), V <sub>BATT_REG</sub> = 4.2V, TERM_EN = b'1, T <sub>A</sub> = 0°C to 70°C	130	160	190	mA
Automatic recharge battery voltage threshold	V <sub>RECH</sub>	V <sub>BATT</sub> falling, VRECHG (03h, bit[0]) = b'0, T <sub>A</sub> = 0°C to 70°C	70	100	130	mV
		V <sub>BATT</sub> falling, VRECHG = b'1, T <sub>A</sub> = 0°C to 70°C	150	200	250	mV
Battery OVP threshold	V <sub>BATT_OVP</sub>	V <sub>BATT</sub> rising, V <sub>BATT_REG</sub> = 4V, T <sub>A</sub> = 0°C to 70°C	102	104	105.5	% of V <sub>BATT_REG</sub>
Battery OVP hysteresis	V <sub>BATT_OVP_HYS</sub>	V <sub>BATT</sub> falling		2		%
Battery OCP in discharge mode	I <sub>DSCHG_OCP</sub>	V <sub>BATT</sub> = 4V, BATT_FET_OCP_EN (08h, bit[2]) = b'1, T <sub>A</sub> = 0°C to 70°C	3.95	4.5	5.05	A
Battery MOSFET (BATFET) on resistance	R <sub>DS(ON)_QBATT</sub>			30		mΩ
<b>Thermal Regulation and Protection</b>						
Junction temperature regulation	T <sub>J_REG</sub>	TREG (0Ch, bits[7:5]) = 80°C		80		°C
		TREG = 120°C		120		°C
Thermal shutdown rising junction temperature	T <sub>J_SHDN</sub>	Rising temperature		150		°C
Thermal shutdown hysteresis	T <sub>SHDN_HYS</sub>	Falling temperature		30		°C
<b>Battery Temperature Monitoring (JEITA)</b>						
NTC cold temperature rising threshold	V <sub>COLD</sub>	VCOLD (0Bh, bits[1:0]) = 74.2% (0°C), T <sub>A</sub> = 0°C to 70°C	73.7	74.2	74.7	% of V <sub>NTC</sub>
NTC cold temperature rising threshold hysteresis	V <sub>COLD_HYS</sub>			1.4		% of V <sub>NTC</sub>
NTC cool temperature rising threshold	V <sub>COOL</sub>	VCOOL (0Bh, bits[3:2]) = 64.8% (10°C), T <sub>A</sub> = 0°C to 70°C	64.3	64.8	65.3	% of V <sub>NTC</sub>
NTC cool temperature hysteresis	V <sub>COOL_HYS</sub>			1.4		% of V <sub>NTC</sub>
NTC warm temperature falling threshold	V <sub>WARM</sub>	VWARM (0Bh, bits[5:4]) = 29.1% (50°C), T <sub>A</sub> = 0°C to 70°C	28.6	29.1	29.6	% of V <sub>NTC</sub>
NTC warm temperature hysteresis	V <sub>WARM_HYS</sub>			1.4		% of V <sub>NTC</sub>

**ELECTRICAL CHARACTERISTICS (continued)**
**V<sub>IN</sub> = 5V, T<sub>A</sub> = -40°C to +125°C, unless otherwise noted.**

Parameters	Symbol	Condition	Min	Typ	Max	Units
NTC hot temperature falling threshold	V <sub>HOT</sub>	V <sub>HOT</sub> (0Bh, bits[7:6]) = 23% (60°C), T <sub>A</sub> = 0°C to 70°C	22	23	24	% of V <sub>NTC</sub>
NTC hot temperature hysteresis	V <sub>HOT_HYS</sub>			1.4		% of V <sub>NTC</sub>
NTC float threshold	V <sub>NTC_FLT</sub>			90		% of V <sub>NTC</sub>
NTC float hysteresis	V <sub>NTC_FLT_HYS</sub>			1.4		% of V <sub>NTC</sub>
NTC reference voltage	V <sub>NTC</sub>			1		V
<b>Input Voltage and Current Regulation</b>						
Input minimum voltage regulation	V <sub>IN_LIM</sub>		3.9		5.4	V
Input minimum voltage limit accuracy	V <sub>IN_LIM_ACC</sub>	V <sub>IN_LIM</sub> = 3.9V, T <sub>A</sub> = 0°C to 70°C	3.75	3.9	4.05	V
		V <sub>IN_LIM</sub> = 4.5V, T <sub>A</sub> = 0°C to 70°C	4.35	4.5	4.65	V
Input current limit range	I <sub>IN_LIM_RANGE</sub>	I <sub>IN_LIM</sub> adjustable via the I <sup>2</sup> C, 100mA/step, default 500mA	100		3200	mA
Input current limit accuracy	I <sub>IN_LIM_ACC</sub>	I <sub>IN_LIM</sub> = 500mA, T <sub>A</sub> = 0°C to 70°C	420	465	500	mA
		I <sub>IN_LIM</sub> = 900mA, T <sub>A</sub> = 0°C to 70°C	790	845	900	mA
		I <sub>IN_LIM</sub> = 1.5A, T <sub>A</sub> = 0°C to 70°C	1320	1410	1500	mA
		I <sub>IN_LIM</sub> = 3A, T <sub>A</sub> = 0°C to 70°C	2680	2840	3000	mA
<b>Boost Mode and Discharge Mode</b>						
Boost regulation voltage range	V <sub>BOOST_RANGE</sub>		4		6	V
Low battery voltage threshold in boost mode	V <sub>BATT_LOW</sub>	BATT_LOW_TH (08h, bits[5:4]) = b'10 (2.9V), T <sub>A</sub> = 0°C to 70°C	2.75	2.9	3.05	V
		BATT_LOW_TH = b'01 (2.7V), T <sub>A</sub> = 0°C to 70°C	2.55	2.7	2.85	V
Low battery voltage threshold hysteresis in boost mode	V <sub>BATT_LOW_HYS</sub>			200		mV
OTG over-current limit range	I <sub>OTG_OCL_RANGE</sub>		0.5		1.5	A
OTG over-current limit accuracy	I <sub>OTG_OCL_ACC</sub>	OTG_ILIM (0Eh, bits[5:4]) = b'00, V <sub>BATT</sub> = 4V, T <sub>A</sub> = 0°C to 70°C	500			mA
		OTG_ILIM = b'11, V <sub>BATT</sub> = 4V, T <sub>A</sub> = 0°C to 70°C	1500			mA
Boost OVP threshold	V <sub>BOOST_OVP</sub>	Boost mode, V <sub>OUT</sub> rising, T <sub>A</sub> = 0°C to 70°C	6.1	6.5	6.99	V
Boost OVP threshold hysteresis	V <sub>BOOST_OVP_HYS</sub>	Boost mode, V <sub>OUT</sub> falling		300		mV
Battery UVLO threshold	V <sub>BATT_UVLO</sub>	T <sub>A</sub> = 0°C to 70°C	2.39	2.5	2.61	V

**ELECTRICAL CHARACTERISTICS (continued)**
**V<sub>IN</sub> = 5V, T<sub>A</sub> = -40°C to +125°C, unless otherwise noted.**

Parameters	Symbol	Condition	Min	Typ	Max	Units
Battery UVLO hysteresis	V <sub>BATT_UVLO_HYS</sub>			400		mV
Automatic boost threshold range	V <sub>IN_AUTO-BOOST_TH</sub>	V <sub>IN</sub> falling from 5V, V <sub>BATT</sub> = 4V	3.9		4.8	V
Automatic boost threshold accuracy	V <sub>IN_AUTO-BOOST_TH_ACC</sub>	V <sub>IN</sub> falling from 5V, V <sub>BATT</sub> = 4V, V <sub>IN_RM_TH</sub> (0Dh, bits[2:1]) = b'00 (3.9V), T <sub>A</sub> = 0°C to 70°C	-1.3		+1.7	% of set value
<b>Logic I/O for the SCL, SDA, /INT, and /DISC Pins</b>						
Logic-low input voltage	V <sub>IL</sub>				0.4	V
Logic-high input Voltage	V <sub>IH</sub>		1.3			V
Open-drain low output voltage	V <sub>OUT_L</sub>	I <sub>SNK</sub> = 10mA			0.2	V
<b>D+/D- Detection</b>						
DCD D+ pull-up current	I <sub>DP_SRC</sub>		6	10	14	μA
DCD D- pull-down resistance	R <sub>DM_DWN</sub>		15.5	20	24.5	kΩ
D+/D- low source voltage	V <sub>SRC_LOW</sub>		540	600	660	mV
D+/D- sink current	I <sub>SNK</sub>		48	100	152	μA
Data detect voltage	V <sub>DAT_REF</sub>		290	350	410	mV
<b>Fault Deglitch Timers</b>						
Boosting deglitch time during low battery	t <sub>D_BATT_LOW</sub>	V <sub>BATT</sub> falling	9.5	10	10.5	ms
Battery UVLO deglitch time	t <sub>BATT_UVLO_DGL</sub>	V <sub>BATT</sub> falling	9.5	10	10.5	μs
Battery OV deglitch time	t <sub>BATT_OV_DGL</sub>	V <sub>BATT</sub> rising		100		ms
<b>Transition Timers</b>						
Charge termination deglitch time	t <sub>TERM_DGL</sub>		225	250	275	ms
Automatic recharge deglitch time	t <sub>RECHG_DGL</sub>		225	250	275	ms
Top-off timer	t <sub>TOPOFF_TMR</sub>	TOPOFF_TMR (19h, bits[3:2]) = b'01	13.5	15	16.5	min
		TOPOFF_TMR = b'10	27	30	33	min
		TOPOFF_TMR = b'11	40	45	50	min
<b>BATFET Control Timer</b>						
Wake-up time in shipping mode	t <sub>WAKE</sub>	T_WAKE (18h, bits[1:0]) = b'00	0.45	0.5	0.55	s
		T_WAKE = b'01	0.9	1	1.1	s
		T_WAKE = b'10	1.8	2	2.2	s
		T_WAKE = b'11	3.6	4	4.4	s
BATFET turn-off time	t <sub>DISC</sub>	T_DISC (18h, bits[5:4]) = b'00	0.9	1	1.1	s
		T_DISC = b'01	1.8	2	2.2	s
		T_DISC = b'10	3.6	4	4.4	s
		T_DISC = b'11	7.2	8	8.8	s

**ELECTRICAL CHARACTERISTICS** *(continued)*
 $V_{IN} = 5V$ ,  $T_A = -40^{\circ}C$  to  $+125^{\circ}C$ , unless otherwise noted.


Parameters	Symbol	Condition	Min	Typ	Max	Units
<b>Safety Timer</b>						
Watchdog timer	$t_{WD}$	WD_CFG (07h, bits[6:5]) = b'01 (40s)	36	40	44	s
		WD_CFG = b'10 (80s)	72	80	88	s
		WD_CFG = b'11 (160s)	144	160	176	s
Pre-charge timer	$t_{PRECHG\_TMR}$		1.8	2	2.2	hrs
Fast-charge timer	$t_{FAST\_TMR}$	FULL_CHG_TMR (19h, bits[6:5]) = b'01 (5hrs)	4.5	5	5.5	hrs
		FULL_CHG_TMR = b'10 (10hrs)	9	10	11	hrs
		FULL_CHG_TMR = b'11 (15hrs)	13.5	15	16.5	hrs

## TYPICAL CHARACTERISTICS

$V_{IN} = 5V$ ,  $V_{BATT} = \text{full range}$ , I<sup>2</sup>C-controlled,  $I_{CC} = 0.5A$  to  $2A$ ,  $I_{IN\_LIM} = 0.5A$ ,  $V_{IN\_MIN} = 4.5V$ ,  $L = 1.5\mu H$  (DCR = 35m $\Omega$ ),  $T_A = 25^\circ C$ , unless otherwise noted.


### Efficiency vs. Charge Current

$V_{IN} = 5V$ ,  $V_{BATT} = 3.8V$ , CC charge




### Efficiency vs. Charge Current

$V_{IN} = 5V$ ,  $V_{BATT} = 4.2V$ , CV charge




### Battery-Full Voltage vs. Temperature




### CC Charger Current vs. Temperature

$I_{CC} = 500mA$ ,  $V_{BATT} = 3.8V$




### CC Charge Current vs. Temperature

$I_{CC} = 2000mA$ ,  $V_{BATT} = 3.8V$







### Pre-Charger Current vs. Temperature

$I_{PRE} = 50mA$



**TYPICAL CHARACTERISTICS (continued)**

$V_{IN} = 5V$ ,  $V_{BATT} = \text{full range}$ , I<sup>2</sup>C-controlled,  $I_{CC} = 0.5A$  to  $2A$ ,  $I_{IN\_LIM} = 0.5A$ ,  $V_{IN\_MIN} = 4.5V$ ,  $L = 1.5\mu H$   
 (DCR = 35mΩ),  $T_A = 25^\circ C$ , unless otherwise noted.




## TYPICAL PERFORMANCE CHARACTERISTICS

$V_{IN} = 5V$ ,  $V_{BATT} = \text{full range}$ , I<sup>2</sup>C-controlled,  $I_{CC} = 0.5A$  to  $2A$ ,  $I_{IN\_LIM} = 0.5A$ ,  $V_{IN\_MIN} = 4.5V$ ,  $L = 1.5\mu H$  (DCR =  $35m\Omega$ ),  $T_A = 25^\circ C$ , unless otherwise noted.


### Adapter Plugged In

$I_{CC} = 1A$ ,  $V_{BATT} = 3.8V$ , dedicated charging port (DCP) adapter inserted




### Adapter Plugged In

$I_{CC} = 1A$ ,  $V_{BATT} = 3.8V$ , USB standard downstream port (SDP) inserted




### Battery Charge Profile

$I_{IN\_LIM} = 1.5A$ ,  $I_{CC} = 1A$ , Q<sub>R</sub> and Q<sub>L</sub> are off




### Battery Charge Profile

$I_{IN\_LIM} = 1.5A$ ,  $I_{CC} = 1A$ ,  
 $I_{BOOST1} = I_{BOOST2} = 0.5A$




### Charge Steady State

$V_{BATT} = 3.8V$ ,  $I_{IN\_LIM} = 1.5A$ ,  $I_{CC} = 1A$ ,  
 $I_{BOOST1} + I_{BOOST2} = 1A$



### Charge Steady State

$V_{BATT} = 3.8V$ ,  $I_{IN\_LIM} = 1.5A$ ,  $I_{CC} = 1A$ ,  
 $I_{SYS} = 2A$




**TYPICAL PERFORMANCE CHARACTERISTICS (continued)**


$V_{IN} = 5V$ ,  $V_{BATT} = \text{full range}$ , I<sup>2</sup>C-controlled,  $I_{CC} = 0.5A$  to  $2A$ ,  $I_{IN\_LIM} = 0.5A$ ,  $V_{IN\_MIN} = 4.5V$ ,  $L = 1.5\mu H$   
 (DCR = 35m $\Omega$ ),  $T_A = 25^\circ C$ , unless otherwise noted.

**Buck Enabled**


$V_{BATT} = 3.8V$ ,  $I_{IN\_LIM} = 3.2A$ ,  $I_{CC} = 0.5A$ ,  
 $I_{SYS} = 2A$


**Buck Disabled**


$V_{BATT} = 3.8V$ ,  $I_{IN\_LIM} = 3.2A$ ,  $I_{CC} = 0.5A$ ,  
 $I_{SYS} = 2A$


**Charge Enabled**


$V_{BATT} = 3.8V$ ,  $I_{IN\_LIM} = 3.2A$ ,  $I_{CC} = 0.5A$ ,  
 $I_{SYS} = 0A$


**Charge Disabled**


$V_{BATT} = 3.8V$ ,  $I_{IN\_LIM} = 3.2A$ ,  $I_{CC} = 0.5A$ ,  
 $I_{SYS} = 0A$


**SYS Load Transient**

$V_{BATT} = 3.8V$ ,  $I_{IN\_LIM} = 1.5A$ ,  $I_{CC} = 1A$ ,  
 $I_{SYS} = 0A$  to  $0.5A$ ,  $I_{BOOST1} + I_{BOOST2} = 1A$


**V<sub>IN</sub> OVP**

$V_{BATT} = 3.8V$ ,  $I_{IN\_LIM} = 3.2A$ ,  $I_{CC} = 0.5A$ ,  
 $I_{SYS} = 1A$




**TYPICAL PERFORMANCE CHARACTERISTICS (continued)**


$V_{IN} = 5V$ ,  $V_{BATT} = \text{full range}$ , I<sup>2</sup>C-controlled,  $I_{CC} = 0.5A$  to  $2A$ ,  $I_{IN\_LIM} = 0.5A$ ,  $V_{IN\_MIN} = 4.5V$ ,  $L = 1.5\mu H$   
 (DCR = 35mΩ),  $T_A = 25^\circ C$ , unless otherwise noted.

**Load Switch OCP**


$V_{BATT} = 3.3V$ ,  $I_{IN\_LIM} = 1.5A$ ,  $I_{CC} = 1A$ ,  
 $I_{SYS} = 0A$ ,  $I_{BOOST1} = 0.9A$


**SYS SCP**


$V_{BATT} = 2.5V$ ,  $I_{IN\_LIM} = 3.2A$ ,  $I_{PRE} = 100mA$ ,  
 $I_{SYS} = 2A$


**SYS Automatic Reset Mode**


$V_{BATT} = 3.8V$ ,  $I_{IN\_LIM} = 1.5A$ ,  
 $I_{CC} = 0.5A$ ,  $I_{SYS} = 0A$ ,  
 $T_{SYS\_LOW} (18h, \text{bits}[3:2]) = 0.5s$


**Battery Discharging OCP in Idle State**


$V_{BATT} = 3.7V$


**Boost Mode and OTG Mode Enabled**

$V_{BATT} = 3.8V$ ,  $V_{BOOST} = 5V$ ,  $I_{OTG\_LIM} = 1.5A$ ,  
 $I_{OTG} = 1.5A$


**Boost Mode and Load Switch Enabled**

$V_{BATT} = 3.8V$ ,  $V_{BOOST} = 5V$ ,  
 $I_{BOOST1} + I_{BOOST2} = 1A$



**TYPICAL PERFORMANCE CHARACTERISTICS (continued)**

V<sub>IN</sub> = 5V, V<sub>BATT</sub> = full range, I<sup>2</sup>C-controlled, I<sub>CC</sub> = 0.5A to 2A, I<sub>IN\_LIM</sub> = 0.5A, V<sub>IN\_MIN</sub> = 4.5V, L = 1.5μH (DCR = 35mΩ), T<sub>A</sub> = 25°C, unless otherwise noted.


**Boost to Buck Transient**

V<sub>BATT</sub> = 3.8V, V<sub>BOOST</sub> = 5V, V<sub>IN</sub> = 5V, insert V<sub>IN</sub> during boost operation

 CH2: V<sub>PMID</sub> + 3V

 CH3: V<sub>SYS</sub> + 3V

 CH1: V<sub>IN</sub>


 CH4: I<sub>L</sub>

**Boost to Buck Transient**

V<sub>BATT</sub> = 3.8V, V<sub>BOOST</sub> = 5V, V<sub>IN</sub> = 5V, enable the boost function before removing V<sub>IN</sub>

 CH2: V<sub>PMID</sub> + 3V

 CH3: V<sub>SYS</sub> + 3V

 CH1: V<sub>IN</sub>


 CH4: I<sub>L</sub>

**Shipping Mode Entry/Exit through /DISC**

V<sub>BATT</sub> = 3.8V, T<sub>DISC</sub> (18h, bits[5:4]) = 2s, BATTFET\_DLY (18h, bits[7:6]) = 4s, T<sub>WAKE</sub> (18h, bits[1:0]) = 2s

 CH1: V<sub>CC</sub>

 CH2: V<sub>SYS</sub>

CH3: /DISC


 CH4: I<sub>BATT</sub>

**NTC JEITA Protection**

V<sub>BATT</sub> = 3.95V, I<sub>CC</sub> = 0.5A, JEITA\_ISET = 50%, JEITA\_VSET = -250mV

 CH1: V<sub>NTC</sub>

 CH3: V<sub>sw</sub>

 CH2: V<sub>SYS</sub>

 CH4: I<sub>BATT</sub>


### FUNCTIONAL BLOCK DIAGRAM




Figure 2: Functional Block Diagram

## OPERATION

The MP2772 is a highly integrated, bidirectional, switch-mode battery charger for 1-cell Li-ion battery applications. The device integrates an input reverse blocking MOSFET ( $Q_B$ ), high-side MOSFET (HS-FET, also called  $Q_{HS}$ ), low-side MOSFET (LS-FET, also called  $Q_{LS}$ ), battery MOSFET (BATFET, also called  $Q_{BATT}$ ), and load switches ( $Q_R$  and  $Q_L$ ) (see Figure 2 on page 20).

### Main States

The MP2772 operates in 5 main states, described below:

- **Idle state:** The MP2772 provides power to the system load only through the battery. The input USB power is not present, and buck or boost switching is not active.
- **Buck idle state (Hi-Z mode):** The input power ( $P_{IN}$ ) is present, and buck switching is not active. The MP2772 remains in buck idle state, also known as high-impedance (Hi-Z) state. The load switches are also off.
- **Buck switching state:** Buck switching is active with a valid input source. Battery charging and load switch powering are allowed in this state.
- **Boost switching state:** Boost switching is active, and the battery discharges. On-the-go (OTG) mode or the load switches can be selected to power the load.
- **Shipping mode state:** The MP2772's BATFET turns off, and the IC consumes the minimum amount of power from the battery.

### Power Supply

The VCC pin supplies internal biasing circuitry as well as the  $Q_{HS}$  and  $Q_{LS}$  gate driver. VCC can also be used as the pull-up rail for the /INT pin or /CE pin. The higher value between the input voltage ( $V_{IN}$ ), battery voltage ( $V_{BATT}$ ), and PMID voltage ( $V_{PMID}$ ) is selected internally to power up the low-dropout (LDO) regulator, which has  $V_{CC}$  as its output.

### Device Power from the Input Source

When the input source is plugged in, the MP2772 detects the input source before buck

mode switching is enabled. The input source must meet the following requirements:

1.  $V_{IN} > V_{BATT} + V_{HDRM}$
2.  $V_{IN\_UVLO} < V_{IN} < V_{IN\_OVLO}$

Once the input power source meets the above conditions, input power good (PG) is detected, and the VIN\_PG\_STAT bit (15h, bit[7]) is set to 1 to indicate a PG condition. As the VIN state changes, the VIN\_PG\_FLAG bit (10h, bit[7]) is set to 1. If the flag is not cleared, the VIN\_PG\_FLAG bit remains at 1, even when the VIN state changes. Write 1 to the flag bit to clear it.

### Idle State

When the input power source is not present and the battery is connected where  $V_{BATT}$  exceeds the under-voltage (UV) battery voltage ( $V_{BATT\_UV}$ ),  $Q_{BATT}$  turns on and starts up the system. The MP2772 features a low on resistance ( $R_{DS(ON)}$ ) BATFET with a low quiescent current ( $I_Q$ ) gate driver, which maintains low power consumption while extending battery life. The discharge over-current protection can be optionally enabled or disabled by setting the BATT\_FET\_OCP\_EN bit (08h, bit[2]). The over-current protection (OCP) threshold can be determined via the one-time programmable (OTP) memory.

### Buck Idle State (Hi-Z Mode)

There are two ways to enter buck idle state, describe below:

1. If the BUCK\_EN bit (00h, bit[3]) is set to 0, the MP2772 enters buck idle (Hi-Z) mode with an adapter present. The device enters low input  $I_Q$  state with the internal biasing circuitry,  $Q_B$ , and load switches turned off.
2. If the BUCK\_EN bit is set to 1,  $V_{IN}$  is below the sum of  $V_{BATT}$  and the input headroom. Under this condition,  $V_{IN}$  is too low to support normal buck switching, and the IC enters buck idle state.

### Input Power Path Automatic Control

When a valid input power source is present,  $Q_B$  automatically turns on; when the input power is removed,  $Q_B$  automatically turns off.

$Q_B$  is also controlled to turn off automatically under certain abnormal events, such as entering buck idle mode or  $V_{IN}$  over-voltage protection (OVP) state.

### Input Current Limit Setting

To prevent the input adapter from being overloaded, the MP2772 supports several methods for setting the input current limit ( $I_{IN\_LIM}$ ). If the input current ( $I_{IN}$ ) increases and reaches  $I_{IN\_LIM}$ , then the charge current is reduced to prioritize the system power, and the load switches power.

#### Method 1: Pin-Controlled

If the `ILIM_PIN_EN` bit (01h, bit[2]) is set to 1,  $I_{IN\_LIM}$  is set by the logic on the `ILIM` pin. A logic high on the `ILIM` pin sets  $I_{IN\_LIM}$  to 2.5A, and a logic low on the `ILIM` pin sets  $I_{IN\_LIM}$  to 0.5A.

#### Method 2: Register-Controlled

If the `ILIM_PIN_EN` bit is set to 0,  $I_{IN\_LIM}$  is set by either the Battery Charging 1.2 (BC1.2) detection results or via the `IIN_LIM` (02h, bits[7:3]) bits. If BC1.2 is disabled by setting the `USB_DET_EN` bit (0Fh, bit[6]) to 0 and the `ILIM_RECONFIG` bit (04h, bit[0]) to 1, then  $I_{IN\_LIM}$  is set by the `IIN_LIM` bits. If BC1.2 is enabled by setting the `USB_DET_EN` bit to 1 and the `ILIM_RECONFIG` bit to 0, then  $I_{IN\_LIM}$  is set by the BC1.2 detection results.

The `ILIM_PIN_EN` bit is set to 1. It is necessary to set the `ILIM_PIN_EN` bit to 0 first to use the USB BC1.2 detection results to set  $I_{IN\_LIM}$ . In addition, the `ILIM_RECONFIG` bit must be set to 1 to set  $I_{IN\_LIM}$  via the I<sup>2</sup>C.

### USB Battery Charging 1.2 (BC1.2) Detection

The MP2772 initiates BC1.2 detection if the following conditions are met:

- $V_{IN}$  power is present
- The `USB_DET_EN` bit is set to 1

BC1.2 detection can differentiate between the standard downstream port (SDP, with a 500mA  $I_{IN\_LIM}$ ), dedicated charging port (DCP, with a 1.8A  $I_{IN\_LIM}$ ), and charging downstream port (CDP, with a 1.5A  $I_{IN\_LIM}$ ) to set  $I_{IN\_LIM}$  accordingly. If plugging in the adapters that are not compliant with BC1.2, the MP2772 detects the input source as an unknown type, and  $I_{IN\_LIM}$  is set to 500mA for safety considerations.

After detection is finished, the input source type is reported via the `VIN_STAT` bits (15h, bits[1:0]).

### Input Voltage Limit Setting

The MP2772 supports the configurable input voltage limit ( $V_{IN\_LIM}$ ) set via the `VIN_LIM` bits (03h, bits[6:3]). When  $V_{IN}$  drops to the configured limit due to the input source's limited power capability, the  $V_{IN}$  loop closes, and the charge current is reduced to prioritize the system power.


### Buck Converter and Charger Operation

Once BC1.2 detection is complete, if the `BUCK_EN` bit is set to 1, the buck converter initiates soft start (SS). The buck converter's switching frequency ( $f_{SW}$ ) can be selected between 1.5MHz and 2MHz, based on the `FRE_SEL` bit (00h, bit[2]) setting. Peak current mode control is adopted to regulate the system voltage ( $V_{SYS}$ ), battery charge current, battery regulation voltage,  $I_{IN\_LIM}$ ,  $V_{IN\_LIM}$ , and the device's die temperature loops.

The MP2772 automatically starts charging if the `CHG_EN` bit (00h, bit[5]) is set to 1.

### Narrow-Voltage DC (NVDC) Power Path Management

Figure 3 shows the narrow-voltage DC (NVDC) power path management structure.




**Figure 3: NVDC Power Path Management Structure**

With this structure,  $Q_{BATT}$  decouples the system from the battery and controls battery charging and discharging separately. The MP2772 prioritizes the system (SYS) output using the power path function, which selects between the input source and battery, or uses both.

When input source is removed,  $Q_{BATT}$  turns on fully to pass the battery power to the system with a low-impedance path.

When the input source is present and the buck converter starts up, the system output is related to  $V_{BATT}$ . Figure 4 shows the  $V_{SYS}$  variation with  $V_{BATT}$  when charging is enabled and disabled.



**Figure 4:  $V_{SYS}$  Variation with  $V_{BATT}$**

The steps of the charging process according to  $V_{BATT}$  are described below:

1. When the battery is below the minimum system voltage ( $V_{SYS\_MIN}$ ) set by the `SYS\_MIN\_REG` bits (07h, bits[3:1]),  $V_{SYS}$  is regulated at the sum of  $V_{SYS\_MIN}$  and battery tracking voltage 1 ( $V_{TRACK1}$ ) (150mV).  $Q_{BATT}$  works in linear mode to charge the battery with trickle-charge, pre-charge, or fast-charge current, depending on  $V_{BATT}$ .
2. As  $V_{BATT}$  starts to exceed  $V_{SYS\_MIN}$ ,  $Q_{BATT}$  turns on fully.
3. When the charge is suspended or completed ( $Q_{BATT}$  is turned off), the system voltage is regulated at the sum of  $V_{SYS\_MIN}$  and  $V_{TRACK1}$  (150mV) if  $V_{BATT}$  is below  $V_{SYS\_MIN}$ ; the system voltage is regulated at the sum of  $V_{BATT}$  and battery tracking

voltage 2 ( $V_{TRACK2}$ ) when  $V_{BATT}$  exceeds  $V_{SYS\_MIN}$ .

### Dynamic Power Management

To avoid overloading the input power source, the MP2772 features dynamic power management (DPM) by continuously monitoring  $I_{IN}$  and  $V_{IN}$ . When the  $I_{IN\_LIM}$  threshold or  $V_{IN\_LIM}$  threshold is reached, the battery charge current is reduced to prevent the input source from overloading and to prioritize the system power, load switches' power, or both.

When the IC is operating in the  $I_{IN\_LIM}$  loop or the  $V_{IN\_LIM}$  loop, the `INLIM\_STAT` bit (15h, bit[6]) or the `VINLIM\_STAT` bit (15h, bit[5]) is set accordingly. The `INPUT\_LMT\_FLAG` bit (10h, bit[3]) is set to 1, and the interrupt alert is generated if the `INPUT\_LMT\_MASK` bit (13h, bit[3]) is set to 0 (not masked). If the interrupt is masked, the `INPUT\_LMT\_FLAG` bit remains at 1 while there is no interrupt generated.

If the charge current drops to 0A and the system voltage continues dropping while the system load increases, once the system voltage drops below  $V_{BATT}$ , the MP2772 automatically enters supplement mode.

### Battery Supplement Mode

When the system voltage drops below  $V_{BATT}$ ,  $Q_{BATT}$  turns on to prevent the system voltage from further dropping, and the MP2772 enters battery supplement mode. In this mode, the buck converter and the battery provide power to the system together. If the battery supplies power to the system, then an ideal diode is implemented by forcing the voltage across the BATFET to be 20mV. This facilitates the transition between the BATFET and DC/DC converter.

For load switches powering loads that exceed the input source capacity, the battery cannot enter supplement mode to discharge and power the load switches' loading with the input. Battery supplement mode is only provided for system overload conditions.

If  $V_{BATT}$  is below the battery UVLO threshold ( $V_{BATT\_UVLO}$ ), then supplement mode is not available. Under this condition,  $V_{SYS}$  can only be powered by the DC/DC converter.

Therefore, the DC/DC converter is not allowed to be disabled, as the microcontroller unit (MCU) powered by  $V_{SYS}$  loses I<sup>2</sup>C control. The system may enter a locked state until the user removes the input source and inserts it again to exit the locked state.

### Battery Charging Profile

The MP2772 can autonomously run a battery charge cycle without requiring the MCU host. Alternatively, the host can control the charging parameters via the registers.


A new charge cycle is initiated if the following conditions are met:

- The buck converter starts up.

- The NTC pin voltage ( $V_{NTC}$ ) is within the valid temperature range.
- There is no safety timer fault.
- Charging is enabled by pulling the /CE pin low or setting the CHG\_EN bit to 1.

The MP2772 checks  $V_{BATT}$  to provide four charging phases: trickle charge, pre-charge, constant-current charge, constant-voltage charge, and optional top-off charge. By default, top-off charge is disabled.

Figure 5 shows the full battery charging profile.



**Figure 5: Battery Charging Profile**

### Charging Phases

#### Phase 1: Trickle Charge

When  $P_{IN}$  is qualified as a good power supply, the MP2772 checks  $V_{BATT}$  to determine whether trickle charge is required. If  $V_{BATT}$  is below its trickle-charge voltage ( $V_{BATT\_TC}$ ) (2.2V), then the trickle-charge current ( $I_{TC}$ ) is applied on the battery, which helps reset the protection circuit in the battery pack.  $I_{TC}$  can be set via the ITRICKLE bits (02h, bits[2:0]).

#### Phase 2: Pre-Charge

When  $V_{BATT}$  exceeds  $V_{BATT\_TC}$ , the MP2772 starts to safely pre-charge the deeply depleted battery until  $V_{BATT}$  reaches the pre-charge to fast charge threshold ( $V_{BATT\_PRE}$ ). If  $V_{BATT\_PRE}$  is not reached before pre-charge timer (2hrs) expires, then the charge cycle ends, and a corresponding timeout fault signal is asserted.

The pre-charge current ( $I_{PRE}$ ) can be configured via the IPRE bits (05h, bits[7:4]), which ranges between 10mA and 160mA.

#### Phase 3: Constant-Current (CC) Fast Charge

When  $V_{BATT}$  exceeds  $V_{BATT\_PRE}$ , which is set via the VPRE bits (03h, bits[2:1]), the MP2772 enters into constant-current (CC) fast charge phase. The fast charge current ( $I_{CC}$ ) can be configured via the ICC bits (04h, bits[7:1]). There are two stages during fast charge. Firstly, the BATTERY FET works linearly to charge the battery with  $I_{CC}$ . When  $V_{BATT}$  exceeds  $V_{SYS\_MIN}$ , the BATTERY FET turns on fully. The charge current loop is implemented by the buck converter's pulse-width modulation (PWM) control.

**Phase 4: Constant-Voltage Charge**

When  $V_{BATT}$  rises to the configurable float voltage ( $V_{BATT\_REG}$ ), which is set via the VBATT\_REG bits (06h, bits[6:0]), the charge current begins to taper off.

**Charge Termination**

The charge cycle is considered complete when the charge current reaches the battery termination threshold ( $I_{TERM}$ ), which is set via the ITERM bits (05h, bits[3:0]).

Termination occurs if the following conditions are met:

- The termination function is enabled by setting the TERM\_EN bit (CTRL\_CFG\_0, bit[1]) to 1.
- The charge current is below the termination threshold for the charge termination deglitch time ( $t_{TERM\_DGL}$ ) (250ms).
- Charging is in constant-voltage phase.
- The device is not in any power limiting state, including  $I_{IN\_LIM}$ ,  $V_{IN\_LIM}$ , and thermal regulation.

Since top-off timer operation is disabled by default, the MP2772 enters the charge done state immediately after termination occurs. The charge status bits, CHG\_STAT (15h, bits[4:2]), are set to charge done state, and the interrupt signal bit, CHG\_DONE\_FLAG (10h, bit[6]), is set to 1 to send a signal interrupt to indicate charging is complete.

If the top-off timer is enabled, the MP2772 enters the top-off state first, then enters the charge done state after the top-off timer expires.

**Top-Off Timer Operation**

To further charge the battery after the termination current threshold is crossed and  $t_{TERM\_DGL}$  expires, a configurable top-off timer can be used to automatically extend the charging time. The TOPOFF\_TMR bits (19h, bits[3:2]) configure the top-off timer, including the top-off timer disable.

When the TOPOFF\_TMR bits setting exceeds 0, charging continues until the timer expires. Then charging is terminated, and an interrupt is sent.

The top-off timer is reset when any of the following conditions occur:

- Charging is enabled from the disabled state.
- The recharge condition is triggered.
- Register reset is triggered.

**Charging Enable Methods**

To allow a flexible control scheme for the charging enable, the BATFET can be turned on via either bit or pin control.

Pin control is enabled when the PIN\_CTRL\_EN bit (01h, bit[4]) is set to 1. Pull the /CE pin low to enable the BATFET and initiate battery charging.

If the PIN\_CTRL\_EN bit is set to 0, the CHG\_EN bit is written to 1 to generate the charge enable signal.

**Recharge Operation**

When the battery is fully charged and charging is terminated, the battery may be discharged through the leakage current. After  $V_{BATT}$  discharges and falls to the automatic recharge battery voltage threshold ( $V_{BATT\_REG} - V_{RECH}$ ), the MP2772 can automatically start another charging cycle if  $P_{IN}$  is present and the RCHG\_EN bit (06h, bit[7]) is set to 1. A 250ms deglitch timer is applied for detecting  $V_{BATT}$  dropping below the recharge threshold.

After charging is terminated, input source re-plugin or re-enabling charging also starts a new charging cycle.

**Shipping Mode**

In applications where the battery is not removable, it is essential to disconnect the battery from the system to enter shipping mode. Shipping mode is valid without the input present. When the input is present, entering shipping mode via the register and pin control are invalid but entering shipping mode is recorded. Shipping mode entry is active after the input is removed.

### Entering Shipping Mode via the Register

Write 1 to the BATTFET\_DIS bit (0Fh, bit[1]).

If the BATTFET\_DLY bits (18h, bits[7:6]) are set to b'0, the IC immediately enters shipping mode. If the BATTFET\_DLY bits are not set to 0, the device waits for the time specified in the bits before entering shipping mode.

### Entering Shipping Mode via Pin Control


The /DISC pin can be used to enter shipping mode. To enter shipping mode through the hardware, the SYS\_RST\_MODE bit (0Fh, bit[2]) must be set to 0. If there is no P<sub>IN</sub> present, pull down the /DISC pin for a longer period than the duration set by the T\_DISC bits (18h, bits[5:4]) to enter shipping mode.

### Exiting Shipping Mode

There are two ways to exit shipping mode, described below:

- **Method 1:** Plug in the input power source to make the part exit shipping mode automatically and initiate input detection operation.
- **Method 2:** If the device is in shipping mode, pull down the /DISC pin for a longer period than the duration set by the T\_WAKE bits (BAT\_FET\_CRTL, bits[1:0]) to wake up the device from shipping mode.


Figure 6 shows how to enter and exit shipping mode by pulling the /DISC pin down in the hardware mode.



**Figure 6: Shipping Mode Entry and Exit via the /DISC Pin**

### System Pin Power Reset

When the SYS\_RST\_MODE bit is set to 1, pull the /DISC pin down to trigger automatic reset. This resets the power on the MCU connected to the SYS pin by turning off the BATFET for the time period set via the T\_SYS\_LOW bits (18h, bits[3:2]), then turns the BATFET back on. Figure 7 shows the timing diagram of the SYS pin power reset.



**Figure 7: Timing Diagram of the SYS Pin Power Reset**

If VIN is inserted, in automatic reset mode, the DC/DC converter also turns off to shut down the SYS pin voltage (V<sub>SYS</sub>) to trigger the power reset function. To recover V<sub>SYS</sub> to normal operation, two conditions must be met:

1. The /DISC pin is released.
2. The system's off time exceeds the period set by T\_SYS\_LOW bits.

### Register Reset

Write 1 to the REG\_RST bit (00h, bit[7]) resets all registers to the OTP values (OTP-backed) or default values (non-OTP backed).

### Watchdog

After start-up, the MP2772 operates with the default set-up. The watchdog timer is disabled by default. Once the watchdog is enabled, write 1 to the WD\_RST bit (07h, bit[7]) to restart the watchdog timer counter. The watchdog timer period is 40s, 80s, or 160s, which are configurable via the WD\_CFG bits (07h, bits[6:5]).

The WD\_ACT bit (07h, bit[4]) defines the behavior of a watchdog timer fault. If the WD\_ACT bit is set to 0, the watchdog only resets the register when it times out. If the WD\_ACT bit is set to 1, the watchdog not only resets the register but also turns off the BATFET and the DC/DC converter for the time period set via the T\_SYS\_LOW bits, then re-enables the BATFET to reset the system power at the SYS pin.

### Load Switch Operation

The MP2772 integrates two load switches (Q<sub>R</sub> and Q<sub>L</sub>) that can supply power to the load during either buck operation or boost operation. The load switches are powered through the PMID pin and can be turned on/off separately via the LDSW\_EN bits (0Eh, bits[7:6]).

The load switches are only allowed to turn on during boost mode or buck mode. The LDSW\_EN bits do not turn on the load switches during idle or Hi-Z (buck idle) mode.

### Boost Start-Up Conditions

The MP2772 enables boost switching if the following conditions are met:

- $V_{BATT} > BATT\_LOW\_TH$  (08h, bits[5:4])
- Boost is enabled either by setting the PIN\_CTRL\_EN bit (01h, bit[4]) to 0 and the BOOST\_EN bit (00h, bit[4]) to 1, or by setting the PIN\_CTRL\_EN bit to 1 and setting the BST\_EN pin to logic high.

### Boost Operation

The boost voltage ( $V_{BOOST}$ ) loop regulates  $V_{PMID}$  based on the setting of the VBOOST bits (0Dh, bits[7:3]). The voltage regulation step size is 100mV/step. The highest  $V_{BOOST}$  is 6V, and the lowest  $V_{BOOST}$  is selected as the higher value between  $V_{BATT} + 200mV$  and lowest VBOOST bits setting (4V). For example, if  $V_{BATT}$  is 4.2V, the lowest  $V_{BOOST}$  is 4.4V. If  $V_{BATT}$  is 3V, the lowest  $V_{BOOST}$  is 4V. Boost operation can either provide power to  $Q_R$  and  $Q_L$ , or it can provide power back to the USB input referred to as the OTG function.

### Boost On-The-Go (OTG Function)

Once the boost converter starts up and  $V_{PMID}$  is stable, the blocking MOSFET ( $Q_B$ ) can be turned on to supply power through the USB port if the OTG\_EN bit (00h, bit[6]) is set to 1 and boost switching is enabled by either bit or pin control.

### Boost Load Switch Function

Once the boost converter starts up and  $V_{PMID}$  is stable,  $Q_R$  and  $Q_L$  can be turned on by writing 1 to the LDSW\_EN bits.

Due to the boost converter's power constraints, the boost load switch function and OTG function cannot be turned on at the same time. If both functions are enabled, the operation chooses to provide power through  $Q_R$  and  $Q_L$  as the higher priority.

### Boost Light-Load Condition Detection

To minimize power consumption and extend battery life, the MP2772 implements a boost light-load detection function by using the analog-to-digital converter (ADC) to monitor the current through  $Q_R$  and  $Q_L$ . If the current flowing through  $Q_R$  and  $Q_L$  is below the preset light-load threshold set via the BST\_LIGHT\_LD\_TH bits (1Ah, bits[6:5]), a light-load condition is detected. An interrupt flag via the BOOST\_LD\_FLAG bit (11h, bit[0]) is asserted upon detection. The boost light-load condition detection is enabled by setting the LD\_DET bit (1Ah, bit[7]) to 1.

### Automatic Buck-Boost Transition

#### Buck to Boost Transition

If both buck and boost switching are enabled, the input removal detection function is activated, and the device can automatically transition from buck operation to boost operation.

When  $P_{IN}$  is removed, as  $V_{IN}$  drops below the threshold set via the VIN\_RM\_TH bits (0Dh, bits[2:1]), the input blocking MOSFET turns off, and the boost converter starts to switch. The boost converter is on for a minimum of 0.5s before the IC checks the  $V_{IN}$  conditions again. If  $V_{IN}$  exceeds the threshold set via the VIN\_TH\_RM bits again, operation resumes to charge. In most conditions,  $V_{IN}$  remains below the threshold set via the VIN\_RM\_TH bits. The boost lasts for the operation. This function blocks the VIN\_RM\_TH bits to work for a minimum of 0.5s. This avoids buck and boost transition oscillation.

#### Boost to Buck Transition

During boost operation, if  $V_{IN}$  is plugged in, the input detection circuit starts to validate the input power source and perform BC1.2 detection. After detection is done, the input blocking MOSFET turns on, the boost converter stops switching, and the device enters buck operation.

### Analog-to-Digital Converter (ADC) Operation

There are two types of data used for ADC operation: status data and decision data.

The MP2772 integrates an 8-bit ADC to report status information on  $V_{IN}$ ,  $I_{IN}$ , the system voltage,  $V_{BATT}$ , battery charge current, and load switch voltage. The ADC also senses the decision data on the NTC pin and current through the individual load switches (below 100mA).

Write b'1 to the ADC\_START bit (0Fh, bit[4]) to enable the ADC to sample all the ADC channels and update the associated registers.

The ADC\_RDY\_FLAG bit (10h, bit[5]) is generated to signal to the MCU that the ADC data is ready.

The ADC automatically senses the decision data at a rate determined by the ADC\_RATE bit (0Fh, bit[3]) (0.5s/100ms). To enable decision data automatic sampling on the NTC pin or the current (below 100mA) through load switch detection, the following actions must be performed by the host MCU:

- NTC protection or PCB hot protection must be enabled by setting the CHG\_NTC\_EN bits (0Ch, bits[2:1]) to 1, or by setting the PCB\_OTP\_EN bit (01h, bit[1]) to 1.
- The load switch must be enabled by setting the LDSW\_EN bits (0Eh, bits[7:6]) to 01, 10, or 11. These bits should not be set to 00. The load switch current-sense circuitry is enabled by setting the LDSW\_CS\_L\_EN bit (0Eh, bit[3]) to 1, or by setting the LDSW\_CS\_R\_EN bit (0Eh, bit[2]) to 1.

### Analog-to-Digital Converter (ADC) Data

Table 1 shows the data measured by the ADC.

**Table 1: ADC Measurement Data**

Data	Full Scale	Recommended Range	LSB
Battery voltage ( $V_{BATT}$ )	6.375V	2.55V to 5V	25mV
SYS pin voltage ( $V_{SYS}$ )	6.375V	2.55V to 5V	25mV
NTC pin voltage ( $V_{NTC}$ )	1.275V	0V to 1.2V	5mV
Input voltage ( $V_{IN}$ )	10.2V	4.55V to 5.5V	40mV
Trickle charge and pre-charge current	255mA	10mA to 160mA	1mA
Constant-current (CC) charge current (20mA to 320mA)	510mA	20mA to 320mA	2mA
CC charge current (340mA to 2000mA)	2550mA	340mA to 2000mA	10mA
Input current ( $I_{IN}$ )	3.391A	20mA to 3.2A	13.3mA
LDSW load current ( $I_{BOOST1/2}$ )	107mA	0mA to 100mA	0.42mA
LDSW voltage ( $V_{BOOST1/2}$ )	6.375V	4.5V to 5.5V	25mV

## Protections

### **Input Over-Voltage Protection (OVP)**

The input over-voltage lockout (OVLO) threshold is 6.5V. If  $V_{IN}$  exceeds increases this threshold, a 10ms deglitch timer is triggered. After the deglitch timer expires and  $V_{IN}$  remains above the OVLO threshold, the device disables switching and the load switches turn off as well.

The MP2772 also provides a 14V OVP threshold, which is always active. If  $V_{IN}$  exceeds 14V, switching is immediately disabled. After the OVP event is removed, switching is disabled for an additional 5s to prevent repetitive OVP event damage.

### **System Over-Voltage Protection (OVP)**

System OVP ensures that  $V_{SYS}$  does not rise high enough to damage the downstream devices. If the system voltage exceeds the SYS\_OVP\_RI\_TH bits (09h, bits[7:4]), switching is immediately disabled. A 10mA current sink is activated after 500 $\mu$ s of an SYS OVP event to help discharge the SYS pin capacitor ( $C_{SYS}$ ), which discharges the SYS pin.

### **Boost Mode Over-Voltage Protection (OVP)**

During boost operation, when  $V_{PMID}$  exceeds the boost OVP threshold ( $V_{BOOST\_OVP}$ ), the device stops switching until  $V_{PMID}$  drops below the difference between  $V_{BOOST\_OVP}$  and the boost OVP hysteresis ( $V_{BOOST\_OVP\_HYS}$ ).

### **Boost Battery Low Protection**

To protect the battery from being overdrained in boost mode, boost switching automatically turns off when  $V_{BATT}$  is below the BATT\_LOW\_TH setting (2.7V or 2.9V). Battery low protection can also be disabled via the BATT\_LOW\_TH bit.

### **Boost On-The-Go (OTG) Short Protection**

During boost OTG operation, if  $V_{IN}$  drops below the difference between  $V_{PMID}$  and 0.75V due to short or heavy loading, the device turns off the blocking MOSFET immediately and enters hiccup mode. After 600ms passes, boost starts up again and softly turns on the input blocking MOSFET again.

### **Battery Under-Voltage Lockout (UVLO)**

To avoid  $V_{BATT}$  from being deeply discharged, once  $V_{BATT}$  drops below  $V_{BATT\_UVLO}$ ,  $Q_{BATT}$  latches off. To recover from this fault, the input power must be plugged in.

### **Battery Over-Voltage Protection (OVP)**

The battery OV threshold is 4% above the battery float voltage. The deglitch time is 100ms. If a battery OV condition is detected, then charging is disabled.

### **Battery Over-Current Protection (OCP)**

There is an over-current limit (OCL) designed in the MP2772 to avoid system over-current conditions during battery discharging. Once the discharge current exceeds the discharge current limit ( $I_{DSCHG\_LIMIT}$ ), the discharge BATFET turns off and enters hiccup mode. After the 600ms recovery time, the discharge BATFET turns on again. If the fault is persistent and hiccup mode continues occurring 8 consecutive times, the BATFET latches off. The BATFET is re-enabled by replugging the input source or pulling down the /DISC pin longer than the wake-up time in shipping mode ( $t_{WAKE}$ ).

### **Load Switch Over-Current Protection (OCP)**

The load switches ( $Q_R$  and  $Q_L$ ) have configurable OCP thresholds set via the LDSW\_OCP bits (0Eh, bits[1:0]), which are in buck mode. The value is typically at about 850mA in buck mode and 550mA in boost mode for each rail when the LDSW\_OCP bits are set to the maximum 600mA. Once the current through the load switch trips the over-current (OC) threshold, the load switch enters hiccup mode and restarts every 600ms. If the OC condition remains after eight tries, the load switches are latched off. Toggling the enable register bit for the load switch clears the fault and re-enables the load switch.

### **Negative Temperature Coefficient (NTC) Protections**

The MP2772 provides the NTC pin to connect the device to an external thermistor and the VNTC pin as the reference for standard charging NTC protection and JEITA charging NTC protection.

### Standard Charging NTC Protection

If the CHG\_NTC\_EN bits are set to b'01, the device performs standard NTC protection. If the detected NTC temperature is outside of the hot/cold threshold range, charging is disabled, and the charging timers are suspended.

### JEITA Charging NTC Protection

If the CHG\_NTC\_EN bits are set to b'10 or b'11, the configurable JEITA profile is used. There are four temperature thresholds defined by JEITA, which are used in the device: cold, cool, warm, and hot. See the Electrical Characteristics section on page 7 for more details regarding the definitions for the MP2772's JEITA temperature thresholds. JEITA is only active in buck charging mode.

Charging is suspended if the NTC is outside of the hot or cold range. At cool temperatures between the NTC cold temperature rising threshold ( $V_{COLD}$ ) and the NTC cool temperature rising threshold ( $V_{COOL}$ ), the charge current and/or charge voltage are reduced according to the setting of the COOL\_ACT bits (0Ah, bits[5:4]), JEITA\_ISET bits (0Ah, bits[1:0]), and JEITA\_VSET bits (0Ah, bits[3:2]). At warm temperatures between the NTC warm temperature falling threshold ( $V_{WARM}$ ) and the NTC hot temperature falling threshold ( $V_{HOT}$ ), the charge voltage and/or charge current are reduced according to the setting of the WARM\_ACT bits (0Ah, bits[7:6]), JEITA\_ISET bits, and the JEITA\_VSET bits.

### PCB Hot Protection

By setting the PCB\_OTP\_EN bit to 1, the MP2772 activates PCB over-temperature protection for battery charging. During charging, when the NTC hot threshold is reached, charging and the MOSBATFET turn off. Charging resumes once the temperature recovers from the hot condition.

### Thermal Regulation and Thermal Shutdown

The thermal regulation limit is set by the TREG bits (0Ch, bits[7:5]). During battery charging, when the MP2772 reaches its internal junction temperature ( $T_J$ ), the charge current is reduced. During this period, the charging safety timer runs at half-rate and charge termination is blocked.

Thermal shutdown protection is active during all operating states. If the device's internal  $T_J$  rises to the shutdown threshold ( $T_{J\_SHDN}$ ) (150°C), then switching is disabled and the BATFET turns off. The device resumes back to normal operation after  $T_J$  drops to the thermal shutdown hysteresis ( $T_{SHDN\_HYS}$ ) (30°C), which is below  $T_{J\_SHDN}$ .

### Interrupt Flag

The MP2772 has an open-drain output that signals an interrupt alert to the MCU host. The /INT pin is typically pulled low for 256µs to signal that an interrupt condition has occurred. If the INT\_CFG bit (0Fh, bit[7]) is set to 1, when an interrupt is triggered, a 256µs pull-down pulse is generated every 1s until the interrupt is cleared.

There are three interrupt alert commands: INT\_FLAG\_0 (10h), INT\_FLAG\_1 (11h), and INT\_FLAG\_2 (12h). These commands report various operating conditions and the two associated mask commands: INT\_FLAG\_MASK\_0 (13h) and INT\_FLAG\_MASK\_1 (14h). The device sends out an interrupt alert signal only when all the interrupt alert commands are cleared, and the state interrupt mask command is set to 0, which means the interrupt is not masked. To acknowledge and clear the interrupt, write 1 to the asserted interrupt bit in the INT\_FLAG\_0, INT\_FLAG\_1, and INT\_FLAG\_2 commands.

### Missing Battery Detection

The MP2772 detects a missing battery when missing battery detection is enabled by setting the BMA\_DET\_EN bit (01h, bit[0]) to 1. After a missing battery is detected, the interrupt flag of the BATTERY\_MISSING\_STAT bit (16h, bit[6]) and the BATTERY\_MISSING\_FLAG bit (10h, bit[1]) are set to 1. An interrupt signal is generated if it is not masked.

After missing battery detection is enabled, the MP2772 sinks the BAT pin to about 10mA for 10ms between 10s intervals when  $V_{IN}$  is present and the part is waiting for recharge state. If the battery node gets pulled below the recharge threshold, the algorithm continues loading the battery node for an additional 90ms to determine whether it can be discharged below the trickle charge threshold.

If the battery node is discharged below the trickle charge threshold, the algorithm triggers charging. If charging completes within 10s, the battery is determined to be missing.

### I<sup>2</sup>C Interface

The MP2772 uses an I<sup>2</sup>C slave interface for flexible charging parameter configuration and status reporting. The I<sup>2</sup>C interface supports a communication frequency up to 400kps.

The device operates as a slave device with a 72h address, receiving control inputs from the master device such as the microcontroller or digital signal processor.

SDA and SCL are open-drain lines that are connected to the positive supply voltage via a current source or pull-up resistor. When the bus is free, both lines are high. The data on the SDA line must be stable during the clock's high period. The data line's high or low state can only change when the clock signal on the SCL line is low. A clock pulse is generated for each data bit transferred (see Figure 8 on page 32).

All the transactions begin with a start (S) command and stop (P) command via a stop command. A high to low transition on the SDA line while SCL is high defines a start command. A low to high transition on the SDA line when SCL is high defines a stop command (see Figure 9 on page 32).

Start and stop commands are always generated by the master. The bus is considered busy after the start command, then considered free after the stop command. Each byte on the SDA line must be 8 bits long. The number of bytes to be transmitted per transfer is unrestricted. Each byte must be followed by an acknowledge

(ACK) bit. Data is transferred first with the most significant bit (MSB) (see Figure 9 on page 32).

If a slave cannot receive or transmit another complete data byte until it has performed some other function, then the slave can hold the SCL clock line low to force the master into a wait state (clock stretching). Data transfer resumes when the slave is ready for another data byte and release the SCL clock line.

Acknowledge occurs after each byte. The acknowledge bit allows the receiver to signal to the transmitter that the byte is successfully received and another byte may be sent. All clock pulses, including the acknowledge 9th clock pulse, are generated by the master.

The transmitter releases the SDA line during the acknowledge clock pulse, allowing the receiver to pull the SDA line low. The SDA line remains high during the 9th clock pulse, which is referred to as the not acknowledge (NACK) signal. The master can then generate either a stop command to halt the transfer or a repeated start command to start a new transfer. After the start command, a slave address is sent, and this address is 7 bits long, followed by the 8th data direction bit (R/W bit), A 0 indicates a transmission (write), and a 1 indicates a request for data (read). Figure 11 on page 32 shows the complete data transfer. Figure 12 on page 33 shows a single write, Figure 13 on page 33 shows a single read, Figure 14 on page 33 shows a multi-byte write, and Figure 15 on page 33 shows a multi-byte read. If the register address is not defined, the charger IC sends back the not acknowledge signal and returns to idle state. The charger device supports multi-read and multi-write via the I<sup>2</sup>C registers.




Figure 8: Bit Transfer on I<sup>2</sup>C Bus




Figure 9: Start and Stop Commands




Figure 10: Data Transfer on the I<sup>2</sup>C Bus





Figure 11: Complete Data Transfer




From master to slave   
  From slave to master   
 A = Acknowledge (SDA low)    S = Start    P = Stop


**Figure 12: Single Write**


From master to slave   
 A = Acknowledge (SDA low)   
 S = Start

From slave to master   
 /A = Not acknowledge (SDA high)   
 P = Stop

**Figure 13: Single Read**


From master to slave   
  From slave to master   
 A = Acknowledge (SDA low)    S = Start    P = Stop

**Figure 14: Multi-Byte Write**


From master to slave   
 A = Acknowledge (SDA low)   
 S = Start

From slave to master   
 /A = Not acknowledge (SDA high)   
 P = Stop

**Figure 15: Multi-Byte Read**

## SUPPORTED I<sup>2</sup>C COMMANDS

I<sup>2</sup>C Slave Address: 72h

**Legend:** WTD = watchdog, R/W = read/write, R = read-only, OTP-configurable = register's default value can be configured via the one-time programmable (OTP) memory

Command Address	Command Name	Type	Bytes	Description
00h	CTRL_CFG_0	R/W	1	Control configuration 0
01h	CTRL_CFG_1	R/W	1	Control configuration 1
02h	IIN_LIM_CFG	R/W	1	Input current limit configuration
03h	CHG_V_CFG	R/W	1	Charge voltage configuration
04h	CHG_CFG_0	R/W	1	Charging configuration 0
05h	CHG_CFG_1	R/W	1	Charging configuration 1
06h	CHG_CFG_2	R/W	1	Charging configuration 2
07h	SYS_WD_CFG	R/W	1	System watchdog configuration
08h	PROT_CFG_0	R/W	1	Protection configuration
09h	SYS_OVP_CFG	R/W	1	System over-voltage protection (OVP) configuration
0Ah	THRM_PROT_CFG_0	R/W	1	Thermal protection configuration 0
0Bh	THRM_PROT_CFG_1	R/W	1	Thermal protection configuration 1
0Ch	THRM_PROT_CFG_2	R/W	1	Thermal protection configuration 2
0Dh	BOOST_CFG	R/W	1	Boost configuration
0Eh	LDSW_CFG	R/W	1	Load switching configuration
0Fh	OP_CFG	R/W	1	Operation configuration
10h	INT_FLAG_0	R	1	Interrupt flag 0
11h	INT_FLAG_1	R	1	Interrupt flag 1
12h	INT_FLAG_2	R	1	Interrupt flag 2
13h	INT_FLAG_MASK_0	R/W	1	Interrupt flag mask 0
14h	INT_FLAG_MASK_1	R/W	1	Interrupt flag mask 1
15h	STAT_0	R	1	Status register 0
16h	STAT_1	R	1	Status register 1
17h	STAT_2	R	1	Status register 2
18h	BAT_FET_CTRL	R/W	1	Battery MOSFET control
19h	TMR_CFG	R/W	1	Timer configuration
1Ah	BSTOFF_CFG	R/W	1	Boost automatic turn-off configuration
1Bh	VBATT_ADC	R	1	ADC-sensed battery voltage
1Ch	VSYS_ADC	R	1	ADC-sensed system voltage
1Dh	NTC_ADC	R	1	ADC-sensed NTC temperature
1Eh	VIN_ADC	R	1	ADC-sensed input voltage
1Fh	ICHG_ADC	R	1	ADC-sensed charge current
20h	IIN_ADC	R	1	ADC-sensed input current
21h	I_BOOST2_ADC	R	1	ADC-sensed boost 2 current
22h	I_BOOST1_ADC	R	1	ADC-sensed boost 1 current
23h	V_BOOST2_ADC	R	1	ADC-sensed boost 2 output voltage
24h	V_BOOST1_ADC	R	1	ADC-sensed boost 1 output voltage

## REGISTER MAP

### CTRL\_CFG\_0 (00h)

Format: Direct

The CTRL\_CFG\_0 command controls on-the-go (OTG) mode as well as the charge function, boost function, and buck enable control. In addition, this command controls register reset, termination enable, and frequency selection.

Bits	Access	Bit Name	Default	Description
7	R	REG_RST	1'b0	Resets any read/write (R/W) registers that are configurable by the user. 1'b0: Maintains the current setting 1'b1: Resets any R/W registers configurable by the user to the default setting This bit returns to 0 after it is written to 1.
6	R/W	OTG_EN	1'b0	1'b0: OTG mode is disabled 1'b1: OTG mode is enabled This bit enables the input blocking MOSFET in boost switching mode and can be set via the one-time programmable (OTP) memory.
5	R/W	CHG_EN	1'b1	1'b0: Battery charging is disabled 1'b1: Battery charging is enabled This bit can be set via the OTP.
4	R/W	BOOST_EN	1'b0	1'b0: The boost converter is disabled 1'b1: The boost converter is enabled This bit can be set via the OTP.
3	R/W	BUCK_EN	1'b1	1'b0: Buck switching is disabled 1'b1: Buck switching is enabled
2	R/W	FRE_SEL	1'b0	1'b0: The buck charger switches at 1.5MHz 1'b1: The buck charger switches at 2MHz This bit can be set via the OTP.
1	R/W	TERM_EN	1'b1	Enables termination. 1'b0: Termination is disabled 1'b1: Termination is enabled This bit can be set via the OTP.
0	R/W	VIN_TRK_EN	1'b1	0: The input voltage limit ( $V_{IN\_LIM}$ ) loop is fixed 1: $V_{IN\_LIM}$ tracks the maximum between 200mV above the battery voltage ( $V_{BATT}$ ) and the $VIN\_LIM$ bit (03h, bits[6:3]) setting

**CTRL\_CFG\_1 (01h)**
**Format:** Direct

The CTRL\_CFG\_1 command sets the MP2772's address, pin control enable/disable, PCB over-temperature protection, and the missing battery detection function.

Bits	Access	Bit Name	Default	Description
7:5	R	I2C_ADDR	3'b010	3'b000: 70h 3'b001: 71h 3'b010: 72H 3'b011: 73h 3'b100: 74h 3'b101: 75h 3'b110: 76h 3'b111: 77h Default: 72h  The address can only be changed in test mode. The address setting can be selected and fixed in the OTP.
4	R/W	PIN_CTRL_EN	1'b1	1'b0: Pin control is disabled for buck or boost operation 1'b1: Pin control is enabled for buck or boost operation  The /CE and BST_EN pins are enabled when this bit is set to 1. If this bit is set to 0, only the CHG_EN bit (00h, bit[5]) and BOOST_EN (00h, bit[4]) can enable boost switching or battery charging. This bit can be set via the OTP.
3	R/W	BAT_OVP_SNK_EN	1'b0	1'b0: Sink discharge on the BAT pin is not enabled 1'b1: Sink discharge on the BAT pin is enabled
2	R/W	ILIM_PIN_EN	1'b1	1'b0: The input current limit ( $I_{IN\_LIM}$ ) is not set via the ILIM pin 1'b1: $I_{IN\_LIM}$ is set via the ILIM pin  This bit can be set via the OTP.
1	R/W	PCB_OTP_EN	1'b0	1'b0: PCB over-temperature protection is not enabled 1'b1: PCB over-temperature protection is enabled  This bit can be set via the OTP.
0	R/W	BMA_DET_EN	1'b1	1'b0: Missing battery detection is not enabled 1'b1: Missing battery detection is enabled

**IIN\_LIM\_CFG (02h)**
**Format:** Direct

The IIN\_LIM\_CFG command sets the IC's input current limit ( $I_{IN\_LIM}$ ) and the trickle charge current ( $I_{TC}$ ).

Bits	Access	Bit Name	Default	Description
7:3	R/W	IIN_LIM	5'b00100	Sets $I_{IN\_LIM}$ .  Range: 100mA (00000) to 3200mA (11111) Offset: 100mA Step: 100mA Default: 500mA (00100)  The default $I_{IN\_LIM}$ setting can be set via the OTP.
2:0	R/W	ITRICKLE	3'b100	Sets $I_{TC}$ .  Range: 10mA (000) to 70mA (110) Offset: 10mA Default: 50mA (100)  The $I_{TC} > 70mA$ setting is clamped to 70mA. The default $I_{TC}$ can be set via the OTP.

**CHG\_V\_CFG (03h)**
**Format:** Direct

The CHG\_V\_CFG command sets the IC's input voltage limit ( $V_{IN\_LIM}$ ), pre-charge threshold, and the automatic recharge threshold.

Bits	Access	Bit Name	Default	Description
7	R	RESERVED	N/A	Reserved.
6:3	R/W	VIN_LIM	4'b0110	Sets the $V_{IN\_LIM}$ range. Range: 3.9V (0000) to 5.4V (1111) Offset: 3.9V Default: 4.5V (0110) The default value can be set via the OTP.
2:1	R/W	VPRE	2'b11	Sets the pre-charge to constant-current charge battery voltage threshold, where the default is 3V (11). 2'b00: 2.4V 2'b01: 2.6V 2'b10: 2.8V 2'b11: 3V The default value can be set via the OTP.
0	R/W	VRECHG	1'b0	Sets the automatic recharge threshold below the battery-full voltage, where the default is 100mV. 1'b0: 100mV threshold 1'b1: 200mV threshold The default value can be set via the OTP.

**CHG\_CFG\_0 (04h)**
**Format:** Direct

The CHG\_CFG\_0 command sets the constant-charge current ( $I_{CC}$ ) and the method to select  $I_{IN\_LIM}$ .

Bits	Access	Bit Name	Default	Description
7:1	R/W	ICC	7'b0011000	Sets $I_{CC}$ . Range: 20mA (0000000) to 2000mA (1100011) Offset: 20mA Step: 20mA Default: 500mA (0011000) When $I_{CC}$ is set above 2A, it is latched to 2A. The default value can be set via the OTP.
0	R/W	ILIM_RECONFIG	1'b0	When $I_{IN\_LIM}$ is not set via ILIM pin control, this bit determines whether to use the USB Battery Charging 1.2 (BC1.2) detection results or the IIN_LIM bit value (set via 02h, bits[7:3]) to set $I_{IN\_LIM}$ . If BC1.2 is disabled and ILIM pin control is disabled, this bit is set to 0 and has no effect, and $I_{IN\_LIM}$ is determined by the IIN_LIM bits (02h, bits[7:3]) setting. 1'b0: Use $I_{IN\_LIM}$ configured as the BC1.2 detection value 1'b1: Use the IIN_LIM bit setting for the $I_{IN\_LIM}$ reference This bit can be set via the OTP.

**CHG\_CFG\_1 (05h)**
**Format:** Direct

The CHG\_CFG\_1 command sets the pre-charge current ( $I_{PRE}$ ) and the charge termination current ( $I_{TERM}$ ).

Bits	Access	Bit Name	Default	Description
7:4	R/W	IPRE	4'b1001	Sets $I_{PRE}$ . Range: 10mA (0000) to 160mA (1111) Offset: 10mA Step: 10mA Default: 100mA (1001) The default value can be set via the OTP.
3:0	R/W	ITERM	4'b1001	Sets $I_{TERM}$ . Range: 10mA (0000) to 160mA (1111) Offset: 10mA Step: 10mA Default: 100mA (1001) The default value can be set via the OTP.

**CHG\_CFG\_2 (06h)**
**Format:** Direct

The CHG\_CFG\_2 command sets the regulation battery voltage ( $V_{BATT\_REG}$ ).

Bits	Access	Bit Name	Default	Description
7	R/W	RCHG_EN	1'b1	1'b0: Automatic recharge function is disabled 1'b1: Automatic recharge function is enabled This bit can be set via the OTP.
6:0	R/W	VBATT_REG	7'b0111 100	Sets $V_{BATT\_REG}$ . Range: 3.6V (0000000) to 4.6V (1100100) Offset: 3.6V Step: 10mV Default: 4.2V (0111100) When $V_{BATT\_REG}$ is set over 4.6V, it is latched to 4.6V. The default value can be set via the OTP.

**SYS\_WD\_CFG (07h)**
**Format:** Direct

The SYS\_WD\_CFG command sets the watchdog timer and the minimum system regulation voltage ( $V_{SYS\_MIN\_REG}$ ).

Bits	Access	Bit Name	Default	Description
7	R/W	WD_RST	1'b0	Write 1 to this bit to reset the watchdog timer.
6:5	R/W	WD_CFG	2'b00	2'b00: Disables the timer 2'b01: 40s 2'b10: 80s 2'b11: 160s Default: Watchdog is disabled (00) The default setting can be set by OTP.

4	R/W	WD_ACT	1'b0	1'b0: The R/W register that can be reset by watchdog timeout reloads to the default setting 1'b1: The R/W register that can be reset by watchdog timeout reloads to the default setting and power is cycled on the SYS pin Default: The R/W register that can be reset by watchdog timeout reloads to the default setting  The default setting can be via the OTP.
3:1	R/W	SYS_MIN_REG	3'b010	Sets V <sub>SYS_MIN_REG</sub> . Range: 3.2V (000) to 4.25V (111) Offset: 3.2V Step: 150mV Default: 3.5V (010)  The default value can be set via the OTP.
0	R	RESERVED	N/A	Reserved.

**PROT\_CFG\_0 (08h)**
**Format:** Direct

The PROT\_CFG\_0 command sets the input over-voltage protection (OVP) threshold and the low V<sub>BATT</sub> threshold for OTG mode. This command also enables protection control.

Bits	Access	Bit Name	Default	Description
7:6	R/W	RESERVED	N/A	Reserved.
5:4	R/W	BATT_LOW_TH	2'b10	Disables boost discharge when V <sub>BATT</sub> is below the low voltage threshold.  2'b00: Disabled. No low voltage threshold to disable the boost converter 2'b01: 2.7V 2'b10: 2.9V 2'b11: 2.9V Default: 2.9V (10)  The default value can be set via the OTP.
3	R/W	SYS_OVP_EN	1'b1	1'b0: System OVP is disabled 1'b1: System OVP is enabled Default: System OVP is enabled (1)  The default value can be set via the OTP.
2	R/W	BATT_FET_OCP_EN	1'b1	1'b0: Battery MOSFET (BATFET) discharge over-current protection (OCP) is disabled 1'b1: BATFET discharge OCP is enabled Default: Enabled (1)  The default value can be set via the OTP.
1	R/W	BATT_OVP_EN	1'b1	1'b0: Battery OVP is disabled 1'b1: Battery OVP is enabled Default: Battery OVP is enabled (1)  The default value can be set via the OTP.
0	R	RESERVED	N/A	Reserved.

**SYS\_OVP\_CFG (09h)**
**Format:** Direct

The SYS\_OVP\_CFG command sets the system OVP rising and falling thresholds.

Bits	Access	Bit Name	Default	Description
7:4	R/W	SYS_OVP_RI_TH	4'b1010	Sets the system OVP rising threshold. Range: 3.8V (0000) to 5.3V (1111) Offset: 3.8V Step: 100mV Default: 4.8V(1010)  The default value can be set via the OTP.
3:0	R/W	SYS_OVP_FL_TH	4'b1010	Sets the system OVP recovery falling threshold. Range: 3.6V (0000) to 5.1V (1111) Offset: 3.6V Step: 100mV Default: 4.6V(1010)  The default value can be set via the OTP.

**THRM\_PROT\_CFG\_0 (0Ah)**
**Format:** Direct

The THRM\_PROT\_CFG\_0 command sets the JEITA protection actions.

Bits	Access	Bit Name	Default	Description
7:6	R/W	WARM_ACT	2'b01	Sets the protection action at the negative temperature coefficient (NTC) warm temperature.  2'b00: No action 2'b01: Reduces V <sub>BATT_REG</sub> 2'b10: Reduces I <sub>CC</sub> 2'b11: Reduces both V <sub>BATT_REG</sub> and I <sub>CC</sub> Default: Reduces V <sub>BATT_REG</sub> (01)
5:4	R/W	COOL_ACT	2'b10	Sets the protection action at the NTC cool temperature.  2'b00: No action . Charging stops 2'b01: Reduces V <sub>BATT_REG</sub> 2'b10: Reduces I <sub>CC</sub> 2'b11: Reduces both V <sub>BATT_REG</sub> and I <sub>CC</sub> Default: Reduces I <sub>CC</sub> (10)
3:2	R/W	JEITA_VSET	2'b00	2'b00: V <sub>BATT_REG</sub> - 100mV 2'b01: V <sub>BATT_REG</sub> - 150mV 2'b10: V <sub>BATT_REG</sub> - 200mV 2'b11: V <sub>BATT_REG</sub> - 250mV Default: V <sub>BATT_REG</sub> - 100mV (00)
1:0	R/W	JEITA_ISET	2'b00	2'b00: 50% of I <sub>CC</sub> 2'b01: 33% of I <sub>CC</sub> 2'b10: 25% of I <sub>CC</sub> 2'b11: 16.7% of I <sub>CC</sub> Default: 50% of I <sub>CC</sub> (00)

**THRM\_PROT\_CFG\_1 (0Bh)**
**Format:** Direct

The THRM\_PROT\_CFG\_1 command sets the JEITA protection thresholds.

Bits	Access	Bit Name	Default	Description
7:6	R/W	VHOT	2'b10	Sets the NTC hot falling threshold. 2'b00: 29.1% (50°C) 2'b01: 25.9% (55°C) 2'b10: 23.0% (60°C) 2'b11: 20.4% (65°C) Default: 23% (10)
5:4	R/W	VWARM	2'b10	Sets the NTC warm falling threshold. 2'b00: 36.5% (40°C) 2'b01: 32.6% (45°C) 2'b10: 29.1% (50°C) 2'b11: 25.9% (55°C) Default: 29.1% (10)
3:2	R/W	VCOOL	2'b10	Sets the NTC cool rising threshold. 2'b00: 74.2% (0°C) 2'b01: 69.6% (5°C) 2'b10: 64.8% (10°C) 2'b11: 59.9% (15°C) Default: 64.8% (10)
1:0	R/W	VCOLD	2'b01	Sets the NTC cold rising threshold. 2'b00: 78.4% (-5°C) 2'b01: 74.2% (0°C) 2'b10: 69.6% (5°C) 2'b11: 64.8% (10°C) Default: 74.2% (01)

**THRM\_PROT\_CFG\_2 (0Ch)**
**Format:** Direct

The THRM\_PROT\_CFG\_2 command sets the thermal regulation thresholds and the NTC protection options.

Bits	Access	Bit Name	Default	Description
7:5	R/W	TREG	3'b100	Sets the thermal regulation threshold for charging. 3'b000: 60°C 3'b001: 70°C 3'b010: 8°C 3'b011: 9°C 3'b100: 100°C 3'b101: 11°C 3'b110: 120°C Default: 100°C (100)
4:3	R	RESERVED	N/A	Reserved.
2:1	R/W	CHG_NTC_EN	2'b01	2'b00: Charger NTC monitoring is disabled 2'b01: Charger standard NTC monitoring (only the hot/cold threshold) 2'b10: Charger JEITA NTC monitoring is enabled 2'b11: Charger JEITA NTC monitoring is enabled Default: Standard NTC monitor (01)

0	R	RESERVED	N/A	Reserved.
---	---	----------	-----	-----------

**BOOST\_CFG (0Dh)**
**Format:** Direct

 The BOOST\_CFG command controls the boost output ( $V_{OUT\_BOOST}$ ) voltage as well as the OTG output.

Bits	Access	Bit Name	Default	Description
7:3	R/W	VBOOST	5'b01010	Sets $V_{OUT\_BOOST}$ . Range: 4V to 6V (maximum clamped to 6V) Step: 100mV Offset: 4V Default: 5V (01010) This bit can be set via the OTP
2:1	R/W	VIN_RM_TH	2'b00	Sets the input threshold to initiate automatic boost. 2'b00: 3.9V 2'b01: 4.2V 2'b10: 4.5V 2'b11: 4.8V When input voltage ( $V_{IN}$ ) drops below this threshold, the boost converter automatically turns on, where the default is 3.9V (00). The default value can be set via the OTP.
0	R	RESERVED	N/A	Reserved.

**LDSW\_CFG (0Eh)**
**Format:** Direct

 The LDSW\_CFG command controls the output of the load switches ( $Q_R$  and  $Q_L$ ) as well as the OTG output.

Bits	Access	Bit Name	Default	Description
7:6	R/W	LDSW_EN	2'b00	2'b00: $Q_R$ and $Q_L$ are both disabled 2'b01: $Q_R$ is enabled 2'b10: $Q_L$ is enabled 2'b11: $Q_R$ and $Q_L$ are both enabled Default: $Q_R$ and $Q_L$ are both disabled (00) This bit can be set via the OTP.
5:4	R/W	OTG_ILIM	2'b11	Sets the boost OTG output current limit ( $I_{OTG\_LIM}$ ). 2'b00: 500mA 2'b01: 900mA 2'b10: 1.2A 2'b11: 1.5A Default: 1.5A (11) The default value can be set via the OTP.
3	R/W	LDSW_CS_L_EN	1'b0	1'b0: The current sensing circuitry is disabled for $Q_L$ 1'b1: The current sensing circuitry is enabled for $Q_L$
2	R/W	LDSW_CS_R_EN	1'b0	1'b0: The current sensing circuitry is disabled for $Q_R$ 1'b1: The current sensing circuitry is enabled for $Q_R$

1:0	R/W	LDSW_OCP	2'b11	Sets the over-current limit thresholds for the <b>load switches' output</b> in buck mode. 00: 150mA 01: 300mA 10: 450mA 11: 600mA
-----	-----	----------	-------	-----------------------------------------------------------------------------------------------------------------------------------------------

**OP\_CFG (0Fh)**
**Format:** Direct

The OP\_CFG command provides several controls for the device as well as the ADC setting.

Bits	Access	Bit Name	Default	Description
7	R/W	INT_CFG	1'b0	1'b0: One-shot interrupt pulse 1'b1: Continuous interrupt pulse (1s period)  This bit can be set via the OTP.
6	R/W	USB_DET_EN	1'b1	1'b0: Automatic BC1.2 detection is disabled 1'b1: Automatic BC 1.2 detection is enabled  Toggling this bit can force BC1.2 detection to restart. This bit can be set via the OTP.
5	R/W	VIN_DISCHG_EN	1'b1	Enables the VIN pin automatic discharge when the input is removed.  1'b0: Disabled 1'b1: Enabled
4	R/W	ADC_START	1'b0	1'b0: Disables the ADC 1'b1: Enables the ADC  This bit is written to 1 to trigger a conversion on all ADC channels.
3	R/W	ADC_RATE	1'b0	1'b0: 0.1s ADC sampling rate 1'b1: 0.5s ADC sampling rate
2	R/W	SYS_RST_MODE	1'b1	1'b0: Manual reset. Pull down the /DISC pin to disable the BATFET; the BATFET is not automatically re-enabled 1'b1: Automatic reset. Pull down the /DISC pin to disable the VSYS output, then enable the VSYS output again
1	R/W	BATTFET_DIS	1'b0	1'b0: Enables the BATFET 1'b1: Disables the BATFET  Write 1 to this bit to disable the BATFET after the time specified by the BATTFET_DLY bits (08h, bits[7:6]), then enter shipping mode. This bit control is only valid without V <sub>IN</sub> .
0	R/W	BOX_TIME_EN	1'b0	1'b0: The 10s box time before entering shipping mode is not enabled 1'b1: The 10s box time before entering shipping mode is enabled

**INT\_FLAG\_0 (10h)**
**Format:** Direct

The INT\_FLAG\_0 command shows the interrupt flag of some operation statuses or faults. Write 1 to clear these interrupt flags.

Bits	Access	Bit Name	Default	Description
7	R	VIN_PG_FLAG	1'b0	1'b0: There is no change in the V <sub>IN</sub> power good (PG) status 1'b1: The V <sub>IN</sub> PG status changes
6	R	CHG_DONE_FLAG	1'b0	1'b0: Charging is not finished 1'b1: Charging finished
5	R	ADC_RDY_FLAG	1'b0	1'b0: ADC conversion is not complete 1'b1: ADC conversion is complete
4	R	VIN_DET_FLGA	1'b0	1'b0: V <sub>IN</sub> detection is not complete 1'b1: V <sub>IN</sub> detection is complete
3	R	INPUT_LMT_FLAG	1'b0	1'b0: The device is not in an input limiting state 1'b1: The device enters an input limiting state
2	R	NTC_FAULT_FLAG	1'b0	1'b0: There is no NTC fault 1'b1: There is an NTC fault
1	R	BATTERY_MISSING_FLAG	1'b0	1'b0: A missing battery is not detected 1'b1: A missing battery is detected
0	R	CHG_TMR_FLAG	1'b0	1'b0: There is no charger timer fault 1'b1: A charger timer fault has occurred (either pre-charge or full cycle timer fault)

**INT\_FLAG\_1 (11h)**
**Format:** Direct

The INT\_FLAG\_1 command shows the interrupt flag of some operation status or faults. Write 1 to clear these interrupt flags.

Bits	Access	Bit Name	Default	Description
7	R	WD_FAULT_FLAG	1'b0	1'b0: There is no watchdog timer fault 1'b1: A watchdog timer fault occurred
6	R	BOOST_LOW_FLAG	1'b0	1'b0: There is no boost low battery fault 1'b1: A boost low battery fault occurred
5	R	BOOST_OV_FLAG	1'b0	1'b0: There is no over-voltage (OV) condition for the boost output 1'b1: There is an OV condition for the boost output
4	R	BOOST_PMIUV_FLAG	1'b0	1'b0: There is no under-voltage (UV) condition for the boost output 1'b1: There is an UV condition for the boost output
3	R	OTG_SC_FLAG	1'b0	1'b0: There is no OTG short fault 1'b1: An OTG short fault occurred
2	R	LDSW_OC_FLAG	1'b0	1'b0: There is no over-current (OC) fault for the load switch 1'b1: There is an OC fault for the load switch
1	R	LDSW_OV_FLAG	1'b0	1'b0: There is no OV fault for the load switch 1'b1: There is an OV fault for the load switch
0	R	BOOST_LD_FLAG	1'b0	1'b0: The boost converter is not under a light-load condition 1'b1: The boost converter is under a light-load condition

**INT\_FLAG\_2 (12h)**
**Format:** Direct

The INT\_CFG\_2 command shows the interrupt flag of some operation statuses or faults. Write 1 to clear these interrupt flags.

Bits	Access	Bit Name	Default	Description
7	R	INPUT_OV_FLAG	1'b0	1'b0: There is no OV condition for the input 1'b1: There is an OV condition for the input
6	R	BATTERY_OV_FLAG	1'b0	1'b0: There is no OV battery fault 1'b1: There is an OV battery fault
5	R	SYS_OV_FLAG	1'b0	1'b0: There is no OV condition for the system output 1'b1: There is an OV condition for the system output
4	R	SYS_SC_FLAG	1'b0	1'b0: There is no short-circuit condition for the system output 1'b1: There is a short-circuit condition for the system output
3	R	BATTERY_OCP_FLAG	1'b0	1'b0: There is no OC fault at the BATFET 1'b1: There is an OC fault at the BATFET
2	R	THRM_REG_FLAG	1'b0	1'b0: There is no thermal regulation condition 1'b1: The device operates under a thermal regulation condition
1	R	THRM_SHDN_FLAG	1'b0	1'b0: There is no thermal shutdown condition 1'b1: The device operates under a thermal shutdown condition
0	R	RESERVED	N/A	Reserved.

**INT\_FLAG\_MASK\_0 (13h)**
**Format:** Direct

The INT\_FLAG\_MASK\_0 command determines whether an interrupt is generated when the IC status changes.

Bits	Access	Bit Name	Default	Description
7	R/W	VIN_PG_MASK	1'b1	Masks the V <sub>IN</sub> PG flag. 1'b0: Unmasked 1'b1: Masked
6	R/W	CHG_DONE_MASK	1'b1	Masks the charge done flag. 1'b0: Unmasked 1'b1: Masked
5	R/W	ADC_RDY_MASK	1'b1	Masks the ADC ready flag. 1'b0: Unmasked 1'b1: Masked
4	R/W	VIN_DET_MASK	1'b1	Masks the V <sub>IN</sub> detection flag. 1'b0: Unmasked 1'b1: Masked
3	R/W	INPUT_LMT_MASK	1'b1	Masks the input limit flag. 1'b0: Unmasked 1'b1: Masked
2	R/W	CHG_FAULT_MASK	1'b1	Masks the input OV flag, battery OV flag, system OV flag, system short-circuit flag, and charger timer flag. 1'b0: Unmasked 1'b1: Masked

1	R/W	NTC_FAULT_MASK	1'b1	Masks the NTC fault flag. 1'b0: Unmasked 1'b1: Masked
0	R	RESERVED	N/A	Reserved.

**INT\_FLAG\_MASK\_1 (14h)**
**Format:** Direct

The INT\_FLAG\_MASK\_1 command determines whether an interrupt is generated when the IC status changes.

Bits	Access	Bit Name	Default	Description
7	R/W	TIMER_FAULT_MASK	1'b1	Masks the watchdog fault flag. 1'b0: Unmasked 1'b1: Masked
6	R/W	BOOST_FAULT_MASK	1'b1	Masks the boost low flag, boost OV flag, boost PMID UV flag, and OTG short-circuit flag. 1'b0: Unmasked 1'b1: Masked
5	R/W	BOOST_LD_MASK	1'b1	Masks the boost light-load flag. 1'b0: Unmasked 1'b1: Masked
4	R/W	THRM_FAULT_MASK	1'b1	Masks the thermal shutdown flag and thermal regulation flag. 1'b0: Unmasked 1'b1: masked
3	R/W	LDSW_FAULT_MASK	1'b1	Masks the load switch OC flag and load switch OV flag. 1'b0: Unmasked 1: Masked
2	R/W	BATTERY_OCP_MASK	1'b0	Masks the battery OCP flag. 1'b0: Unmasked 1'b1: Masked
1	R/W	BATTERY_MISSING_MASK	1'b1	Masks the missing battery flag. 1'b0: Unmasked 1'b1: Masked
0	R	RESERVED	N/A	Reserved.

**STAT\_0 (15h)**
**Format:** Direct

The STAT\_0 command shows the operation status.

Bits	Access	Bit Name	Default	Description
7	R	VIN_PG_STAT	1'b0	1'b0: A PG condition is not detected 1'b1: A PG condition is detected
6	R	INLIM_STAT	1'b0	1'b0: The charger is not in an input current limiting state 1'b1: The charger in an input current limiting state
5	R	VINLIM_STAT	1'b0	1'b0: The device is not in a V <sub>IN</sub> limiting state 1'b1: The device is in a V <sub>IN</sub> limiting state

4:2	R	CHG_STAT	3'b000	3'b000: The device is not charging 3'b001: The device is in a trickle charge or pre-charge state 3'b010: Constant-charge (CC) or constant-voltage (CV) state 3'b011: CV loop and I <sub>CHG</sub> < I <sub>TERM</sub> (between CV and charge done/top-off active) deglitch stage before termination 3'b100: Top-off active 3'b101: Charge done 3'b110: Battery OV
1:0	R	VIN_STAT	2'b00	2'b00: V <sub>IN</sub> type unknown 2'b01: Standard downstream port (SDP) detected 2'b10: Charging downstream port (CDP) detected 2'b11: Dedicated charging port (DCP) detected

### STAT\_1 (16h)

**Format:** Direct

The STAT\_1 command shows the operation status.

Bits	Access	Bit Name	Default	Description
7	R	BST_LD_STAT	1'b0	1'b0: The boost converter is not under a light-load condition 1'b1: The boost converter is in a light-load condition  If the load switches' current sense is not enabled, then this bit remains set to 0.
6	R	BATTERY_MISSING_STAT	1'b0	1'b0: The battery is present 1'b1: The battery is missing  If missing battery detection is not enabled, then this bit remains set to 0.
5	R	BOOST_OV_STAT	1'b0	1'b0: No OV condition is present at the boost output 1'b1: An OV condition is present at the boost output
4	R	LDSW_OV_STAT	1'b0	1'b0: No OV condition is present at the load switch output 1'b1: An OV condition is present at the load switch output
3	R	INPUT_OV_STAT	1'b0	1'b0: No OV condition is present at the input 1'b1: An OV condition is present at the input
2	R	SYS_OV_STAT	1'b0	1'b0: No OV condition is present at the system output 1'b1: An OV condition is present at the system output
1:0	R	RESERVED	N/A	Reserved.

### STAT\_2 (17h)

**Format:** Direct

The STAT\_2 command shows the operation status.

Bits	Access	Bit Name	Default	Description
7	R	NTC_MISSING	1'b0	1'b0: There is no fault 1'b1: The NTC is missing
6	R	NTC_COLD	1'b0	1'b0: There is no fault 1'b1: There is an NTC cold fault
5	R	NTC_COOL	1'b0	1'b0: There is no fault 1'b1: There is an NTC cool fault
4	R	NTC_WARM	1'b0	1'b0: There is no fault 1'b1: There is an NTC warm fault
3	R	NTC_HOT	1'b0	1'b0: There is no fault 1'b1: There is an NTC hot fault

2	R	THRM_SHDN_STAT	1'b0	1'b0: There is no fault 1'b1: Thermal shutdown occurs
1	R	THRM_REG_STAT	1'b0	1'b0: Thermal regulation is not active 1'b1: Thermal regulation is active
0	R	RESERVED	N/A	Reserved.

### BAT\_FET\_CTRL (18h)

**Format:** Direct

The BAT\_FET\_CTRL command sets the BATFET on/off control.

Bits	Access	Bit Name	Default	Description
7:6	R/W	BATFET_DLY	2'b11	2'b00: Turn off the BATFET immediately 2'b01: Turn off the BATFET after a 2s delay 2'b10: Turn off the BATFET after a 4s delay 2'b11: Turn off the BATFET after an 8s delay Default: Turn off the BATFET after an 8s delay (11)  The default value can be set via the OTP.
5:4	R/W	T_DISC	2'b01	Sets the glitch filter timeout for the /DISC pin pulled low. Glitch filter expiration triggers turning off the BATFET or cycling power on the SYS pin.  2'b00: 1s 2'b01: 2s 2'b10: 4s 2'b11: 8s Default: 2s (01)  The default value can be set via the OTP.
3:2	R/W	T_SYS_LOW	2'b00	Sets the system low time before re-enabling the BATFET during reset mode.  2'b00: 0.5s 2'b01: 1s 2'b10: 2s 2'b11: 4s Default: 0.5s (00)  The default value can be set via the OTP.
1:0	R/W	T_WAKE	2'b01	Sets the /DISC pin low time to re-enable the BATFET and exit shipping mode.  2'b00: 500ms 2'b01: 1s 2'b10: 2s 2'b11: 4s Default: 1s (01)  The default value can be set via the OTP.

**TMR\_CFG (19h)**
**Format:** Direct

The TMR\_CFG command sets the timer options.

Bits	Access	Name	Default	Description
7	R/W	TMR2x_EN	1'b1	The timer doubles under input limiting states and the thermal regulation state. 1'b0: Disabled 1'b1: Enabled
6:5	R/W	FULL_CHG_TMR	2'b01	2'b00: Disables the timer 2'b01: 5hrs 2'b10: 10hrs 2'b11: 15hrs Default: 5hrs (01)  The default value can be set via the OTP.
4	R/W	PRE_CHG_TMR_EN	1'b1	1'b0: The pre-charge timer is disabled 1'b1: The pre-charge timer is enabled (2hr)  The bit can be set via the OTP.
3:2	R/W	TOPOFF_TMR	2'b00	2'b00: Disabled 2'b01: 15 minutes 2'b10: 30 minutes 2'b11: 45 minutes Default: Disabled (00)  The default value can be set via the OTP.
1:0	R	RESERVED	N/A	Reserved.

**BSTOFF\_CFG (1Ah)**
**Format:** Direct

The BSTOFF\_CFG register sets the boost light load status.

Bits	Access	Bit Name	Default	Description
7	R/W	LD_DET	1'b0	1'b0: The automatic light-load detection function is disabled 1'b1: The automatic light load detection function is enabled
6:5	R/W	BST_LIGHT_LD_TH	2'b00	Sets the boost light-load detection thresholds. The current is measured passing through the load switch during boost switching and once the current drops below the pre-set threshold, a light-load condition is detected. 2'b00: 5mA 2'b01: 10mA 2'b10: 20mA 2'b11: 40mA Default: 5mA (00)  The default value can be set via the OTP.
4:0	R	RESERVED	N/A	Reserved.

**READ-ONLY REGISTERS FOR ADC (8-BIT)**

Address	Name	Description
1Bh	VBATT_ADC	Sensed battery voltage
1Ch	VSYS_ADC	Sensed system voltage
1Dh	NTC_ADC	Sensed NTC voltage
1Eh	VIN_ADC	Sensed input voltage
1Fh	ICHG_ADC	Sensed charge current
20h	IIN_ADC	Sensed input current
21h	I_BOOST2_ADC	Sensed boost 2 (Q <sub>L</sub> ) current
22h	I_BOOST1_ADC	Sensed boost 1 (Q <sub>R</sub> ) current
23h	V_BOOST2_ADC	Sensed boost 2 (Q <sub>L</sub> ) voltage
24h	V_BOOST1_ADC	Sensed boost 1 (Q <sub>R</sub> ) voltage

## APPLICATION INFORMATION

### Selecting the Charge Termination Current

The MP2772 provides a wide range of charge termination current options between 10mA and 160mA for different applications. In addition to the charge current, the MP2772 can supply the system load through its buck converter’s output and its load switches’ outputs. In applications where the input adapter power may be low and the total system output power may be high, the MP2772 activates its input current loop or input voltage loop to prevent overloading the adapter. This action reduces the charge current, which then reduces the battery voltage ( $V_{BATT}$ ) due to the battery pack’s internal resistance ( $R_{BATT}$ ). The battery voltage drop ( $\Delta V_{BATT}$ ) can be calculated with Equation (1):

$$\Delta V_{BATT} = I_{TERM} \times R_{BATT} \quad (1)$$


The combination of the heavy system load and battery internal resistance can result in the MP2772 terminating charging early, and becomes especially evident if  $R_{BATT}$  and the system load are high with a low-capacity input adapter.

Figure 16 shows the charge V-I curve under different system loads, where the input current limit ( $I_{IN\_LIM}$ ) is set to 500mA. With the same charge termination current, a heavier system load may cause charge termination to occur earlier. Setting the charge termination current lower charges the battery as high as possible.


When  $R_{BATT}$  is high, it is recommended to decrease the battery termination threshold ( $I_{TERM}$ ) to minimize  $\Delta V_{BATT}$  as much as possible.

Figure 16 is tested under different battery specifications with varying battery internal resistances ( $R_{BATT} = 50m\Omega$ ,  $100m\Omega$ , or  $150m\Omega$ ). For higher battery internal resistance conditions, setting the charge termination lower is recommended.


In summary, to significantly reduce the impact of heavy system loads and high battery resistance on charge termination, it is recommended to set the charge termination current below 50mA.




(a)



(b)



(c)



**Figure 16: Charge V-I Curve under Different Specifications**

### Selecting the Inductor

Inductor selection is a tradeoff between cost, size, and efficiency. A lower-value inductor corresponds to a smaller size, but also results in a higher current ripple, higher magnetic hysteretic losses, and higher output capacitances. A higher-value inductor results in lower ripple current and smaller output filter capacitors, but also results in higher inductor DC resistance (DCR) loss.

The required inductance (L) can be estimated with Equation (2):

$$L = \frac{V_{IN} - V_{SYS}}{\Delta I_{L\_MAX}} \times \frac{V_{SYS}}{V_{IN} \times f_{SW}} \quad (2)$$

Where  $V_{IN}$  is the input voltage,  $V_{SYS}$  is the converter output voltage,  $f_{SW}$  is the switching frequency, and  $\Delta I_{L\_MAX}$  is the maximum peak-to-peak inductor current, which is typically designed to be between 20% and 40% of the maximum load current.

Choose an inductor that does not saturate under the worst-case load condition. The inductor's saturation current ( $I_{SAT}$ ) can be calculated with Equation (3):

$$I_{SAT} > I_{LOAD} + \frac{\Delta I_{L\_MAX}}{2} \quad (3)$$

Where  $I_{LOAD}$  is the buck converter's maximum load.

### Selecting the PMID Capacitor

The PMID capacitor ( $C_{PMID}$ ) decouples the switching buck converter and absorbs the switching ripple current. Select  $C_{PMID}$  based on the demand for the PMID current ripple. The input current ripple ( $I_{RMS\_MAX}$ ) can be calculated with Equation (4):

$$I_{RMS\_MAX} = I_{LOAD} \times \frac{\sqrt{V_{SYS} \times (V_{IN} - V_{SYS})}}{V_{IN}} \quad (4)$$

Use low-ESR ceramic capacitors with an X7R or X5R rating for  $C_{PMID}$ . This capacitor should be placed as close to the PMID and PGND pins as possible. The capacitor's voltage rating must exceed  $V_{IN}$ , and it is recommended to consider the plug-in overshoot voltage. A capacitor rated for a minimum of 10V is recommended for applications with a 5V  $V_{IN}$ . Generally, a starting capacitance of 10 $\mu$ F is considered sufficient.


### PCB Layout Guidelines

Efficient PCB layout is critical for stable operation and to meet the specified noise, efficiency, and stability requirements. For the best results, refer to Figure 18 and follow the guidelines below:

1. Place the PMID capacitor ( $C_{PMID}$ ) as close to the PMID and PGND pins as possible using a short copper plane connection. Place  $C_{PMID}$  on the same layer as the IC.
2. Minimize the high-frequency current path loop (from the PMID pin to the capacitor to ground; see Figure 17) between  $C_{PMID}$  and the buck converter's power MOSFETs.
3. Place the inductor's input terminal as close to the SW pin as possible.
4. Minimize the copper area of the inductor's input terminal trace to reduce electrical and magnetic field radiation. Ensure that the trace is wide enough to carry the charge current.
5. Minimize parasitic capacitance from the inductor input terminal to any other trace or plane.
6. Place decoupling capacitors (e.g. the VCC pin capacitor) as close to the IC pins as possible, and ensure the connection is as short as possible.
7. Connect the IC's power pins to as many copper planes as possible to conduct heat away from the IC.


8. Ensure that the number and physical size of the vias are sufficient for a current path.

Figure 17 shows a high-frequency current path, which includes the high-side MOSFET, low-side MOSFET, and  $C_{PMID}$ . The high-frequency path must be minimized.




**Figure 17: High-Frequency Current Path**

Figure 18 shows the recommended PCB layout.




**Figure 18: Recommend PCB Layout**

**TYPICAL APPLICATION CIRCUIT**

**Figure 17: Typical Application Circuit**
**Table 2: BOM for Typical Application Circuit**


Qty	Ref	Value	Description	Package	Manufacturer
1	C <sub>IN</sub>	1μF	Ceramic capacitor, 10V, X5R or X7R	0603	Any
2	C <sub>PMID</sub>	10μF	Ceramic capacitor, 10V, X5R or X7R	0805	Any
1	C <sub>SYS</sub>	22μF	Ceramic capacitor, 10V, X5R or X7R	0805	Any
1	C <sub>BATT</sub>	22μF	Ceramic capacitor, 10V, X5R or X7R	0805	Any
1	C <sub>VCC</sub>	1μF	Ceramic capacitor, 10V, X5R or X7R	0603	Any
1	C <sub>BST</sub>	47nF	Ceramic capacitor, 16V, X5R or X7R	0603	Any
1	C <sub>CAP</sub>	100nF	Ceramic capacitor, 16V, X5R or X7R	0603	Any
2	C1, C2	2.2μF	Ceramic capacitor, 10V, X5R or X7R	0603	Any
1	L1	1.5μH	Inductor, 1μH, low DCR	SMD	Any

**PACKAGE INFORMATION**


**WLCSP-30 (2.5mmx2.85mm)**




**TOP VIEW**



**BOTTOM VIEW**




**SIDE VIEW**



**RECOMMENDED LAND PATTERN**

**NOTE:**

- 1) ALL DIMENSIONS ARE IN MILLIMETERS.
- 2) BALL COPLANARITY SHALL BE 0.05 MILLIMETER MAX.
- 3) JEDEC REFERENCE IS MO-211.
- 4) DRAWING IS NOT TO SCALE.

**CARRIER INFORMATION**


Part Number	Package Description	Quantity/ Reel	Quantity/ Tube	Quantity/ Tray	Reel Diameter	Carrier Tape Width	Carrier Tape Pitch
MP2772GC-xxxx-Z	WLCSP-30 (2.5mmx 2.85mm)	5000	N/A	N/A	13in	12mm	8mm

## REVISION HISTORY

Revision #	Revision Date	Description	Pages Updated
1.0	11/11/2024	Initial Release	-

**Notice:** The information in this document is subject to change without notice. Please contact MPS for current specifications. Users should warrant and guarantee that third-party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.